


















Device = LM43602PWPR
Topology = Buck
Created = 7/20/16 11:25:11 PM
BOM Cost = \$2.46
BOM Count = 11
Total Pd = 1.43W

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
10.	U1	Texas Instruments	LM43602PWPR	Switcher	1	\$1.75	 PWP0016F 59 mm ²









Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	628.767 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	214.318 mA	Current	Output capacitor RMS ripple current
3.	Iin Avg	254.81 mA	Current	Average input current
4.	L Ipp	742.42 mA	Current	Peak-to-peak inductor ripple current
5.	BOM Count	11	General	Total Design BOM count
6.	FootPrint	186.0 mm ²	General	Total Foot Print Area of BOM components
7.	Frequency	500.0 kHz	General	Switching frequency
8.	Pout	5.0 W	General	Total output power
9.	Total BOM	\$2.46	General	Total BOM Cost
10.	Low Freq Gain	67.339 dB	Op_Point	Gain at 10Hz
11.	Vout Actual	2.498 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
12.	Vout OP	2.5 V	Op_Point	Operational Output Voltage
13.	Cross Freq	18.325 kHz	Op_point	Bode plot crossover frequency
14.	Duty Cycle	10.959 %	Op_point	Duty cycle
15.	Efficiency	77.483 %	Op_point	Steady state efficiency
16.	Gain Marg	-20.907 dB	Op_point	Bode Plot Gain Margin
17.	IC Tj	75.827 degC	Op_point	IC junction temperature
18.	ICThetaJA	38.9 degC/W	Op_point	IC junction-to-ambient thermal resistance
19.	IOUT_OP	2.0 A	Op_point	Iout operating point
20.	Phase Marg	71.855 deg	Op_point	Bode Plot Phase Margin
21.	VIN_OP	25.0 V	Op_point	Vin operating point
22.	Vout p-p	2.118 mV	Op_point	Peak-to-peak output ripple voltage
23.	Cin Pd	790.696 μW	Power	Input capacitor power dissipation
24.	Cout Pd	111.156 μW	Power	Output capacitor power dissipation
25.	IC Iq Pd	125.0 μW	Power	IC Iq Pd
26.	IC Pd	1.261 W	Power	IC power dissipation
27.	L Pd	191.373 mW	Power	Inductor power dissipation
28.	Total Pd	1.434 W	Power	Total Power Dissipation
29.	Vout Tolerance	2.204 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	2.0	Maximum Output Current
2.	VinMax	25.0	Maximum input voltage
3.	VinMin	21.0	Minimum input voltage
4.	Vout	2.5	Output Voltage
5.	base_pn	LM43602	Texas Instruments Base Part Number
6.	source	DC	Input Source Type
7.	ta	30.0	Ambient temperature

Design Assistance

1. LM43602 Product Folder : <http://www.ti.com/product/LM43602> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).