








## WEBENCH® Design Report







Design : 4372614/11 TPS563209DDCR  
TPS563209DDCR 5.0V-9.0V to 3.30V @ 2.0A




## Electrical BOM

| #  | Name | Manufacturer      | Part Number                          | Properties                                                        | Qty | Price  | Footprint                                                                                                |
|----|------|-------------------|--------------------------------------|-------------------------------------------------------------------|-----|--------|----------------------------------------------------------------------------------------------------------|
| 1. | Cbst | AVX               | 08053C104KAT2A<br>Series= X7R        | Cap= 100.0 nF<br>ESR= 280.0 mOhm<br>VDC= 25.0 V<br>IRMS= 0.0 A    | 1   | \$0.01 | <br>0805 7 mm²        |
| 2. | Cin  | MuRata            | GRM21BR61C106KE15L<br>Series= X5R    | Cap= 10.0 uF<br>ESR= 4.127 mOhm<br>VDC= 16.0 V<br>IRMS= 2.46634 A | 2   | \$0.03 | <br>0805 7 mm²      |
| 3. | Cout | TDK               | C3216JB1A476M<br>Series= JB          | Cap= 47.0 uF<br>ESR= 1.717 mOhm<br>VDC= 10.0 V<br>IRMS= 0.0 A     | 1   | \$0.34 | <br>1206 11 mm²     |
| 4. | L1   | Bourns            | SRN8040-2R2Y                         | L= 2.2 uH<br>DCR= 13.0 mOhm                                       | 1   | \$0.22 | <br>SRN8040 100 mm² |
| 5. | Rfbb | Vishay-Dale       | CRCW040210K0FKED<br>Series= CRCW..e3 | Res= 10.0 kOhm<br>Power= 63.0 mW<br>Tolerance= 1.0%               | 1   | \$0.01 | <br>0402 3 mm²      |
| 6. | Rfbt | Vishay-Dale       | CRCW040233K2FKED<br>Series= CRCW..e3 | Res= 33.2 kOhm<br>Power= 63.0 mW<br>Tolerance= 1.0%               | 1   | \$0.01 | <br>0402 3 mm²      |
| 7. | U1   | Texas Instruments | TPS563209DDCR                        | Switcher                                                          | 1   | \$0.52 | <br>DDC0006A 10 mm² |







## Operating Values

| #   | Name           | Value                 | Category | Description                                                                                |
|-----|----------------|-----------------------|----------|--------------------------------------------------------------------------------------------|
| 1.  | Cin IRMS       | 993.463 mA            | Current  | Input capacitor RMS ripple current                                                         |
| 2.  | Cout IRMS      | 354.526 mA            | Current  | Output capacitor RMS ripple current                                                        |
| 3.  | Iin Avg        | 784.18 mA             | Current  | Average input current                                                                      |
| 4.  | L Ipp          | 1.228 A               | Current  | Peak-to-peak inductor ripple current                                                       |
| 5.  | BOM Count      | 8                     | General  | Total Design BOM count                                                                     |
| 6.  | FootPrint      | 148.0 mm <sup>2</sup> | General  | Total Foot Print Area of BOM components                                                    |
| 7.  | Frequency      | 778.929 kHz           | General  | Switching frequency                                                                        |
| 8.  | Pout           | 6.6 W                 | General  | Total output power                                                                         |
| 9.  | Total BOM      | \$1.17                | General  | Total BOM Cost                                                                             |
| 10. | Vout Actual    | 3.283 V               | Op_Point | Vout Actual calculated based on selected voltage divider resistors                         |
| 11. | Vout OP        | 3.3 V                 | Op_Point | Operational Output Voltage                                                                 |
| 12. | Duty Cycle     | 37.709 %              | Op_point | Duty cycle                                                                                 |
| 13. | Efficiency     | 93.516 %              | Op_point | Steady state efficiency                                                                    |
| 14. | IC Tj          | 55.251 degC           | Op_point | IC junction temperature                                                                    |
| 15. | ICThetaJA      | 62.9 degC/W           | Op_point | IC junction-to-ambient thermal resistance                                                  |
| 16. | IOUT_OP        | 2.0 A                 | Op_point | Iout operating point                                                                       |
| 17. | VIN_OP         | 9.0 V                 | Op_point | Vin operating point                                                                        |
| 18. | Vout p-p       | 4.802 mV              | Op_point | Peak-to-peak output ripple voltage                                                         |
| 19. | Cin Pd         | 2.037 mW              | Power    | Input capacitor power dissipation                                                          |
| 20. | Cout Pd        | 215.808 μW            | Power    | Output capacitor power dissipation                                                         |
| 21. | IC Iq Pd       | 1.507 mW              | Power    | IC Iq Pd                                                                                   |
| 22. | IC Pd          | 401.444 mW            | Power    | IC power dissipation                                                                       |
| 23. | L Pd           | 53.634 mW             | Power    | Inductor power dissipation                                                                 |
| 24. | Total Pd       | 457.616 mW            | Power    | Total Power Dissipation                                                                    |
| 25. | Vout Tolerance | 2.889 %               |          | Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable |

## Design Inputs

| #  | Name | Value | Description            |
|----|------|-------|------------------------|
| 1. | Iout | 2.0   | Maximum Output Current |

| #  | Name    | Value     | Description           |
|----|---------|-----------|-----------------------|
| 2. | VinMax  | 9.0       | Maximum input voltage |
| 3. | VinMin  | 5.0       | Minimum input voltage |
| 4. | Vout    | 3.3       | Output Voltage        |
| 5. | base_pn | TPS563209 | Base Product Number   |
| 6. | source  | DC        | Input Source Type     |
| 7. | Ta      | 30.0      | Ambient temperature   |

## Design Assistance

1. **TPS563209** Product Folder : <http://www.ti.com/product/TPS563209> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

**You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.**

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).