

















Electrical BOM




#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cboot	MuRata	GRM155R61A104KA01D Series= X5R	Cap= 100.0 nF VDC= 10.0 V IRMS= 0.0 A	1	\$0.01	 0402 3 mm ²
2.	Ccomp	MuRata	GRM2165C1H302JA01D Series= C0G/NP0	Cap= 3.0 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.04	 0805 7 mm ²
3.	Ccomp2	MuRata	GRM1555C1H3R9CA01D Series= C0G/NP0	Cap= 3.9 pF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0402 3 mm ²
4.	Cin	MuRata	GRM31CR71H225KA88L Series= X7R	Cap= 2.2 uF ESR= 4.448 mOhm VDC= 50.0 V IRMS= 2.2252 A	1	\$0.05	 1206_190 11 mm ²
5.	Cout	MuRata	GRM31CE70G476ME15L Series= X7U	Cap= 47.0 uF ESR= 3.735 mOhm VDC= 4.0 V IRMS= 4.1841 A	1	\$0.10	 1206_190 11 mm ²
6.	Css	Yageo America	CC0805KRX7R9BB682 Series= X7R	Cap= 6.8 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
7.	D1	Diodes Inc.	B230A-13-F	Vf@Io= 500.0 mV VRRM= 30.0 V	1	\$0.09	 SMA 37 mm ²
8.	L1	Bourns	SRP6540-150M	L= 15.0 uH DCR= 121.0 mOhm	1	\$0.60	 SRP6540 83 mm ²
9.	Rcomp	Vishay-Dale	CRCW040253K6FKED Series= CRCW..e3	Res= 53.6 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
10.	RenB	Vishay-Dale	CRCW040216K9FKED Series= CRCW..e3	Res= 16.9 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
11.	RenT	Vishay-Dale	CRCW0402105KFKED Series= CRCW..e3	Res= 105.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
12.	Rfbb	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
13.	Rfbt	Vishay-Dale	CRCW040228K7FKED Series= CRCW..e3	Res= 28.7 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
14.	Rt	Vishay-Dale	CRCW0402169KFKED Series= CRCW..e3	Res= 169.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
15.	U1	Texas Instruments	TPS54140DGQR	Switcher	1	\$1.26	 S-PDSO-G10 24 mm ²









Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	343.329 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	79.392 mA	Current	Output capacitor RMS ripple current
3.	IC Ipk	1.0 A	Current	Peak switch current in IC
4.	Iin Avg	200.86 mA	Current	Average input current
5.	L Ipp	275.02 mA	Current	Peak-to-peak inductor ripple current
6.	BOM Count	15	General	Total Design BOM count
7.	FootPrint	203.0 mm ²	General	Total Foot Print Area of BOM components
8.	Frequency	682.903 kHz	General	Switching frequency
9.	Pout	3.0 W	General	Total output power
10.	Total BOM	\$2.23	General	Total BOM Cost
11.	D1 Tj	38.054 degC	Op_Point	D1 junction temperature
12.	Low Freq Gain	81.681 dB	Op_Point	Gain at 10Hz
13.	Vout Actual	3.096 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
14.	Vout OP	3.0 V	Op_Point	Operational Output Voltage
15.	Cross Freq	29.778 kHz	Op_point	Bode plot crossover frequency
16.	Duty Cycle	17.607 %	Op_point	Duty cycle
17.	Efficiency	78.609 %	Op_point	Steady state efficiency
18.	Gain Marg	-22.376 dB	Op_point	Bode Plot Gain Margin
19.	IC Tj	52.534 degC	Op_point	IC junction temperature
20.	ICThetaJA	62.5 degC/W	Op_point	IC junction-to-ambient thermal resistance
21.	IOUT_OP	1.0 A	Op_point	Iout operating point
22.	Phase Marg	66.647 deg	Op_point	Bode Plot Phase Margin
23.	VIN_OP	19.0 V	Op_point	Vin operating point
24.	Vout p-p	1.764 mV	Op_point	Peak-to-peak output ripple voltage
25.	Cin Pd	524.307 μ W	Power	Input capacitor power dissipation
26.	Cout Pd	23.542 μ W	Power	Output capacitor power dissipation
27.	Diode Pd	322.177 mW	Power	Diode power dissipation
28.	IC Pd	360.537 mW	Power	IC power dissipation
29.	L Pd	133.1 mW	Power	Inductor power dissipation
30.	Total Pd	816.353 mW	Power	Total Power Dissipation

#	Name	Value	Category	Description
31.	Vout Tolerance	2.513 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	1.0	Maximum Output Current
2.	VinMax	19.0	Maximum input voltage
3.	VinMin	10.0	Minimum input voltage
4.	Vout	3.0	Output Voltage
5.	base_pn	TPS54140	Texas Instruments Base Part Number
6.	source	DC	Input Source Type
7.	ta	30.0	Ambient temperature

Design Assistance

1. TPS54140 Product Folder : <http://www.ti.com/product/TPS54140> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).