






















Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	313.075 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	292.328 mA	Current	Output capacitor RMS ripple current
3.	IC IpK	1.011 A	Current	Peak switch current in IC
4.	Iin Avg	226.98 mA	Current	Average input current
5.	L Ipp	1.012 A	Current	Peak-to-peak inductor ripple current
6.	BOM Count	8	General	Total Design BOM count
7.	FootPrint	75.0 mm ²	General	Total Foot Print Area of BOM components
8.	Frequency	1.321 MHz	General	Switching frequency
9.	Pout	2.5 W	General	Total output power
10.	Total BOM	\$1.51	General	Total BOM Cost
11.	Vout Actual	5.036 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors

#	Name	Value	Category	Description
12.	Vout OP	5.0 V	Op_Point	Operational Output Voltage
13.	Duty Cycle	41.981 %	Op_point	Duty cycle
14.	Efficiency	91.784 %	Op_point	Steady state efficiency
15.	IC Tj	35.752 degC	Op_point	IC junction temperature
16.	ICThetaJA	29.1 degC/W	Op_point	IC junction-to-ambient thermal resistance
17.	IOUT_OP	500.0 mA	Op_point	Iout operating point
18.	VIN_OP	12.0 V	Op_point	Vin operating point
19.	Vout p-p	23.827 mV	Op_point	Peak-to-peak output ripple voltage
20.	Cin Pd	0.0 W	Power	Input capacitor power dissipation
21.	Cout Pd	310.802 μ W	Power	Output capacitor power dissipation
22.	IC Pd	197.663 mW	Power	IC power dissipation
23.	L Pd	25.814 mW	Power	Inductor power dissipation
24.	Total Pd	223.784 mW	Power	Total Power Dissipation
25.	Vout Tolerance	3.53 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	500.0 m	Maximum Output Current
2.	VinMax	12.0	Maximum input voltage
3.	VinMin	10.0	Minimum input voltage
4.	Vout	5.0	Output Voltage
5.	base_pn	TPS62150	Base Product Number
6.	source	DC	Input Source Type
7.	Ta	30.0	Ambient temperature

Design Assistance

1. Feature Highlights: DCS-Control(TM) Architecture with upto 1A output current, 3V to 17V Input Voltage Range, Adjustable output voltage from 0.9V to 6V Selectable operating frequency, Optional Softstart Capacitor for slow startup, Tracking, Pin selectable output voltage (nominal, +5%) Seamless Power Save Mode for Light Load Efficiency, Power Good Output, 100% Duty Cycle mode, Short Circuit Protection, Thermal Shutdown

2. **TPS62150** Product Folder : <http://www.ti.com/product/TPS62150> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).