


## WEBENCH® Design Report





Design : 4737567/3 TPS54335ADDAR  
TPS54335ADDAR 14.0V-22.0V to 3.30V @ 2.0A














## Electrical BOM


| #   | Name   | Manufacturer  | Part Number                          | Properties                                                       | Qty | Price  | Footprint                   |
|-----|--------|---------------|--------------------------------------|------------------------------------------------------------------|-----|--------|-----------------------------|
| 1.  | Cboot  | Kemet         | C0805C104K5RACTU<br>Series= X7R      | Cap= 100.0 nF<br>ESR= 64.0 mOhm<br>VDC= 50.0 V<br>IRMS= 1.64 A   | 1   | \$0.01 | 0805 7 mm <sup>2</sup>      |
| 2.  | Ccomp  | Yageo America | CC0805KRX7R9BB472<br>Series= X7R     | Cap= 4.7 nF<br>VDC= 50.0 V<br>IRMS= 0.0 A                        | 1   | \$0.01 | 0805 7 mm <sup>2</sup>      |
| 3.  | Ccomp2 | Yageo America | CC0805JRNPO9BN101<br>Series= C0G/NP0 | Cap= 100.0 pF<br>VDC= 50.0 V<br>IRMS= 0.0 A                      | 1   | \$0.01 | 0805 7 mm <sup>2</sup>      |
| 4.  | Cin    | MuRata        | GRM31CR61E106KA12L<br>Series= X5R    | Cap= 10.0 uF<br>ESR= 4.512 mOhm<br>VDC= 25.0 V<br>IRMS= 2.447 A  | 1   | \$0.05 | 1206_190 11 mm <sup>2</sup> |
| 5.  | Cinx   | Kemet         | C0805C104K5RACTU<br>Series= X7R      | Cap= 100.0 nF<br>ESR= 64.0 mOhm<br>VDC= 50.0 V<br>IRMS= 1.64 A   | 1   | \$0.01 | 0805 7 mm <sup>2</sup>      |
| 6.  | Cout   | MuRata        | GRM31CR60J107ME39L<br>Series= X5R    | Cap= 100.0 uF<br>ESR= 4.885 mOhm<br>VDC= 6.3 V<br>IRMS= 4.4118 A | 1   | \$0.14 | 1206_190 11 mm <sup>2</sup> |
| 7.  | L1     | Bourns        | SRU1038-100Y                         | L= 10.0 uH<br>DCR= 25.0 mOhm                                     | 1   | \$0.33 | SRU1038 144 mm <sup>2</sup> |
| 8.  | Rcomp  | Vishay-Dale   | CRCW04025K76FKED<br>Series= CRCW..e3 | Res= 5.76 kOhm<br>Power= 63.0 mW<br>Tolerance= 1.0%              | 1   | \$0.01 | 0402 3 mm <sup>2</sup>      |
| 9.  | Rfbb   | Vishay-Dale   | CRCW040232K4FKED<br>Series= CRCW..e3 | Res= 32.4 kOhm<br>Power= 63.0 mW<br>Tolerance= 1.0%              | 1   | \$0.01 | 0402 3 mm <sup>2</sup>      |
| 10. | Rfbt   | Vishay-Dale   | CRCW0402100KFKED<br>Series= CRCW..e3 | Res= 100.0 kOhm<br>Power= 63.0 mW<br>Tolerance= 1.0%             | 1   | \$0.01 | 0402 3 mm <sup>2</sup>      |

| #   | Name | Manufacturer      | Part Number                          | Properties                                          | Qty | Price  | Footprint              |
|-----|------|-------------------|--------------------------------------|-----------------------------------------------------|-----|--------|------------------------|
| 11. | Rt   | Vishay-Dale       | CRCW040295K3FKED<br>Series= CRCW..e3 | Res= 95.3 kOhm<br>Power= 63.0 mW<br>Tolerance= 1.0% | 1   | \$0.01 | 0402 3 mm <sup>2</sup> |
| 12. | U1   | Texas Instruments | TPS54335ADDAR                        | Switcher                                            | 1   | \$0.90 |                        |

R-PDSO-G8 57 mm<sup>2</sup>







## Operating Values

| #   | Name                | Value                 | Category | Description                                                                                |
|-----|---------------------|-----------------------|----------|--------------------------------------------------------------------------------------------|
| 1.  | Cin IRMS            | 739.877 mA            | Current  | Input capacitor RMS ripple current                                                         |
| 2.  | Cout IRMS           | 172.573 mA            | Current  | Output capacitor RMS ripple current                                                        |
| 3.  | Iin Avg             | 355.42 mA             | Current  | Average input current                                                                      |
| 4.  | L Ipp               | 597.81 mA             | Current  | Peak-to-peak inductor ripple current                                                       |
| 5.  | BOM Count           | 12                    | General  | Total Design BOM count                                                                     |
| 6.  | FootPrint           | 262.0 mm <sup>2</sup> | General  | Total Foot Print Area of BOM components                                                    |
| 7.  | Frequency           | 496.814 kHz           | General  | Switching frequency                                                                        |
| 8.  | IC Tolerance        | 12.0 mV               | General  | IC Feedback Tolerance                                                                      |
| 9.  | Pout                | 6.6 W                 | General  | Total output power                                                                         |
| 10. | Total BOM           | \$1.5                 | General  | Total BOM Cost                                                                             |
| 11. | ICThetaJA Effective | 34.0 degC/W           | Op_Point | Effective IC Junction-to-Ambient Thermal Resistance                                        |
| 12. | Low Freq Gain       | 100.743 dB            | Op_Point | Gain at 10Hz                                                                               |
| 13. | Vout Actual         | 3.269 V               | Op_Point | Vout Actual calculated based on selected voltage divider resistors                         |
| 14. | Vout OP             | 3.3 V                 | Op_Point | Operational Output Voltage                                                                 |
| 15. | Cross Freq          | 38.81 kHz             | Op_point | Bode plot crossover frequency                                                              |
| 16. | Duty Cycle          | 16.184 %              | Op_point | Duty cycle                                                                                 |
| 17. | Efficiency          | 84.407 %              | Op_point | Steady state efficiency                                                                    |
| 18. | Gain Marg           | -18.499 dB            | Op_point | Bode Plot Gain Margin                                                                      |
| 19. | IC Tj               | 67.937 degC           | Op_point | IC junction temperature                                                                    |
| 20. | IOUT_OP             | 2.0 A                 | Op_point | Iout operating point                                                                       |
| 21. | Phase Marg          | 56.318 deg            | Op_point | Bode Plot Phase Margin                                                                     |
| 22. | VIN_OP              | 22.0 V                | Op_point | Vin operating point                                                                        |
| 23. | Vout p-p            | 3.299 mV              | Op_point | Peak-to-peak output ripple voltage                                                         |
| 24. | Cin Pd              | 2.47 mW               | Power    | Input capacitor power dissipation                                                          |
| 25. | Cout Pd             | 145.482 $\mu$ W       | Power    | Output capacitor power dissipation                                                         |
| 26. | IC Iq Pd            | 6.82 mW               | Power    | IC Iq Pd                                                                                   |
| 27. | IC Pd               | 1.116 W               | Power    | IC power dissipation                                                                       |
| 28. | L Pd                | 100.745 mW            | Power    | Inductor power dissipation                                                                 |
| 29. | Total Pd            | 1.219 W               | Power    | Total Power Dissipation                                                                    |
| 30. | Vout Tolerance      | 3.049 %               |          | Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable |

## Design Inputs

| #  | Name    | Value     | Description                        |
|----|---------|-----------|------------------------------------|
| 1. | Iout    | 2.0       | Maximum Output Current             |
| 2. | VinMax  | 22.0      | Maximum input voltage              |
| 3. | VinMin  | 14.0      | Minimum input voltage              |
| 4. | Vout    | 3.3       | Output Voltage                     |
| 5. | base_pn | TPS54335A | Texas Instruments Base Part Number |
| 6. | source  | DC        | Input Source Type                  |
| 7. | ta      | 30.0      | Ambient temperature                |

## Design Assistance

1. TPS54335A Product Folder : <http://www.ti.com/product/TPS54335A> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

**You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.**

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).