


WEBENCH® Design Report





Design : 4730153/25 TPS54160ADGQR
TPS54160ADGQR 48.0V-48.0V to 5.00V @ 1.0A















Electrical BOM


#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cboot	MuRata	GRM155R61A104KA01D Series= X5R	Cap= 100.0 nF VDC= 10.0 V IRMS= 0.0 A	1	\$0.01	0402 3 mm ²
2.	Ccomp	MuRata	GRM1885C1H202JA01D Series= C0G/NP0	Cap= 2.0 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	0603 5 mm ²
3.	Ccomp2	MuRata	GRM1555C1H1R5CA01D Series= C0G/NP0	Cap= 1.5 pF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	0402 3 mm ²
4.	Cin	TDK	C3225X7R2A225K230AB Series= X7R	Cap= 2.2 uF ESR= 1.73 mOhm VDC= 100.0 V IRMS= 5.5932 A	1	\$0.19	1210_250 15 mm ²
5.	Cout	MuRata	GRM31CR61A476KE15L Series= X5R	Cap= 47.0 uF ESR= 3.709 mOhm VDC= 10.0 V IRMS= 4.2862 A	1	\$0.15	1206_190 11 mm ²
6.	Css	Yageo America	CC0805KRX7R9BB682 Series= X7R	Cap= 6.8 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
7.	D1	Diodes Inc.	B260A-13-F	VF@Io= 700.0 mV VRRM= 60.0 V	1	\$0.09	SMA 37 mm ²
8.	L1	Bourns	SDR1307-330KL	L= 33.0 uH DCR= 65.0 mOhm	1	\$0.35	SDR1307 227 mm ²
9.	Rcomp	Vishay-Dale	CRCW0402102KFKED Series= CRCW..e3	Res= 102.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	0402 3 mm ²
10.	RenB	Vishay-Dale	CRCW04023K16FKED Series= CRCW..e3	Res= 3.16 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	0402 3 mm ²
11.	RenT	Vishay-Dale	CRCW0402105KFKED Series= CRCW..e3	Res= 105.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	0402 3 mm ²

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
12.	Rfbb	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
13.	Rfbt	Vishay-Dale	CRCW040253K6FKED Series= CRCW..e3	Res= 53.6 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
14.	Rt	Vishay-Dale	CRCW0402249KFKED Series= CRCW..e3	Res= 249.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
15.	U1	Texas Instruments	TPS54160ADGQR	Switcher	1	\$1.55	 S-PDSO-G10 24 mm²









Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	317.916 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	89.706 mA	Current	Output capacitor RMS ripple current
3.	IC Ipk	1.0 A	Current	Peak switch current in IC
4.	Iin Avg	127.36 mA	Current	Average input current
5.	L Ipp	310.75 mA	Current	Peak-to-peak inductor ripple current
6.	BOM Count	15	General	Total Design BOM count
7.	FootPrint	348.0 mm ²	General	Total Foot Print Area of BOM components
8.	Frequency	478.381 kHz	General	Switching frequency
9.	Pout	5.0 W	General	Total output power
10.	Total BOM	\$2.43	General	Total BOM Cost
11.	D1 Tj	41.584 degC	Op_Point	D1 junction temperature
12.	Low Freq Gain	84.925 dB	Op_Point	Gain at 10Hz
13.	Vout Actual	5.088 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
14.	Vout OP	5.0 V	Op_Point	Operational Output Voltage
15.	Cross Freq	29.562 kHz	Op_point	Bode plot crossover frequency
16.	Duty Cycle	11.409 %	Op_point	Duty cycle
17.	Efficiency	81.791 %	Op_point	Steady state efficiency
18.	Gain Marg	-18.469 dB	Op_point	Bode Plot Gain Margin
19.	IC Tj	66.133 degC	Op_point	IC junction temperature
20.	ICThetaJA	62.5 degC/W	Op_point	IC junction-to-ambient thermal resistance
21.	IOUT_OP	1.0 A	Op_point	Iout operating point
22.	Phase Marg	61.609 deg	Op_point	Bode Plot Phase Margin
23.	VIN_OP	48.0 V	Op_point	Vin operating point
24.	Vout p-p	2.311 mV	Op_point	Peak-to-peak output ripple voltage
25.	Cin Pd	174.852 μ W	Power	Input capacitor power dissipation
26.	Cout Pd	29.847 μ W	Power	Output capacitor power dissipation
27.	Diode Pd	463.343 mW	Power	Diode power dissipation
28.	IC Pd	578.126 mW	Power	IC power dissipation
29.	L Pd	71.5 mW	Power	Inductor power dissipation
30.	Total Pd	1.113 W	Power	Total Power Dissipation

#	Name	Value	Category	Description
31.	Vout Tolerance	2.72 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	1.0	Maximum Output Current
2.	VinMax	48.0	Maximum input voltage
3.	VinMin	48.0	Minimum input voltage
4.	Vout	5.0	Output Voltage
5.	base_pn	TPS54160A	Base Product Number
6.	source	DC	Input Source Type
7.	Ta	30.0	Ambient temperature

Design Assistance

1. **TPS54160A** Product Folder : <http://www.ti.com/product/TPS54160A> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).