






















#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
9.	Rfbb	Vishay-Dale	CRCW0402255KFKED Series= CRCW..e3	Res= 255.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	0402 3 mm ²
10.	Rfbt	Vishay-Dale	CRCW04021M00FKED Series= CRCW..e3	Res= 1000.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	0402 3 mm ²
11.	U1	Texas Instruments	LM46002PWPR	Switcher	1	\$1.85	PWP0016F 59 mm ²









Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	570.418 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	192.235 mA	Current	Output capacitor RMS ripple current
3.	Iin Avg	196.15 mA	Current	Average input current
4.	L Ipp	665.92 mA	Current	Peak-to-peak inductor ripple current
5.	BOM Count	13	General	Total Design BOM count
6.	FootPrint	288.0 mm ²	General	Total Foot Print Area of BOM components
7.	Frequency	500.0 kHz	General	Switching frequency
8.	Pout	10.0 W	General	Total output power
9.	Total BOM	\$3.0	General	Total BOM Cost
10.	Low Freq Gain	82.735 dB	Op_Point	Gain at 10Hz
11.	Vout Actual	4.976 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
12.	Vout OP	5.0 V	Op_Point	Operational Output Voltage
13.	Cross Freq	36.731 kHz	Op_point	Bode plot crossover frequency
14.	Duty Cycle	8.833 %	Op_point	Duty cycle
15.	Efficiency	84.693 %	Op_point	Steady state efficiency
16.	Gain Marg	-13.124 dB	Op_point	Bode Plot Gain Margin
17.	IC Tj	94.178 degC	Op_point	IC junction temperature
18.	ICThetaJA	38.9 degC/W	Op_point	IC junction-to-ambient thermal resistance
19.	IOUT_OP	2.0 A	Op_point	Iout operating point
20.	Phase Marg	70.156 deg	Op_point	Bode Plot Phase Margin
21.	VIN_OP	60.0 V	Op_point	Vin operating point
22.	Vout p-p	3.097 mV	Op_point	Peak-to-peak output ripple voltage
23.	Cin Pd	1.916 mW	Power	Input capacitor power dissipation
24.	Cout Pd	44.801 μW	Power	Output capacitor power dissipation
25.	IC Iq Pd	1.62 mW	Power	IC Iq Pd
26.	IC Pd	1.688 W	Power	IC power dissipation
27.	L Pd	117.072 mW	Power	Inductor power dissipation
28.	Total Pd	1.801 W	Power	Total Power Dissipation
29.	Vout Tolerance	1.492 %		Vout Tolerance based on IC Tolerance and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	2.0	Maximum Output Current
2.	VinMax	60.0	Maximum input voltage
3.	VinMin	15.0	Minimum input voltage
4.	Vout	5.0	Output Voltage
5.	base_pn	LM46002	Texas Instruments Base Part Number
6.	source	DC	Input Source Type
7.	ta	30.0	Ambient temperature

Design Assistance

1. LM46002 Product Folder : <http://www.ti.com/product/LM46002> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).