



WEBENCH® Design Report

Design : 3496425/85 UC2844AN
UC2844AN 110.0V-250.0V to 24.00V @ 3.0A








Electrical BOM







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	C12	AVX	08053C104KAT2A Series= X7R	Cap= 100.0 nF ESR= 280.0 mOhm VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
2.	C13	Samsung Electro-Mechanics	CL21C102JBCNFNC Series= C0G/NP0	Cap= 1.0 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
3.	C21	Panasonic	EEV-FK1H331Q Series= FK	Cap= 330.0 uF ESR= 120.0 mOhm VDC= 50.0 V IRMS= 900.0 mA	1	\$0.48	 SM_RADIAL_H13 264 mm ²
4.	C22	Kemet	C0805C220K3GACTU Series= C0G/NP0	Cap= 22.0 pF VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
5.	C23	Yageo America	CC0805KRX7R9BB391 Series= X7R	Cap= 390.0 pF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
6.	Ccs	Samsung Electro-Mechanics	CL21C621JBCNNNC Series= C0G/NP0	Cap= 620.0 pF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
7.	Cin	TDK	B32774D1505K Series= B32774	Cap= 5.0 uF ESR= 9.8 mOhm VDC= 1.3 kV IRMS= 10.5 A	1	\$3.08	 B32774_3150x2200x3650 804 mm ²
8.	Cout1	TDK	B41605A8278M009 Series= 2385	Cap= 2.7 mF ESR= 21.0 mOhm VDC= 63.0 V IRMS= 5.3 A	1	\$12.37	B41605_2500x4000_9 729 mm ²
9.	Cout2	TDK	B41607A8907M008 Series= 2360	Cap= 900.0 uF ESR= 50.0 mOhm VDC= 63.0 V IRMS= 10.2 A	1	\$4.84	B41607_2200x4000_8 576 mm ²
10.	Cref	AVX	08053C104KAT2A Series= X7R	Cap= 100.0 nF ESR= 280.0 mOhm VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
11.	Csc	MuRata	GRM216R71H103KA01D Series= X7R	Cap= 10.0 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
12.	Csnub	TDK	C5750X6S2W225K Series= X6S	Cap= 2.2 uF ESR= 4.3 mOhm VDC= 400.0 V IRMS= 0.0 A	2	NA	 2220 54 mm ²
13.	Ct	Kemet	C0805C102J5GACTU Series= C0G/NP0	Cap= 1.0 nF ESR= 25.0 mOhm VDC= 50.0 V IRMS= 1.71 A	1	\$0.01	 0805 7 mm ²
14.	Cvcc	MuRata	GRM188R61E105KA12D Series= X5R	Cap= 1.0 uF ESR= 17.113 mOhm VDC= 25.0 V IRMS= 979.39 mA	1	\$0.01	 0603 5 mm ²
15.	D21	Diodes Inc.	B260A-13-F	VF@Io= 700.0 mV VRRM= 60.0 V	1	\$0.09	 SMA 37 mm ²
16.	Daux	Diodes Inc.	DFLS1200-7	VF@Io= 850.0 mV VRRM= 200.0 V	1	\$0.21	 PowerDI123 13 mm ²
17.	Dsec	CUSTOM	CUSTOM	VF@Io= 500.0 mV VRRM= 281.398 V	1	NA	CUSTOM 0 mm ²
18.	Dsec2	CUSTOM	CUSTOM	VF@Io= 500.0 mV VRRM= 281.398 V	1	NA	CUSTOM 0 mm ²
19.	Dsnub	Bourns	CD214C-F3600	VF@Io= 1.12 V VRRM= 600.0 V	1	\$0.18	 SMC 83 mm ²
20.	Dz	Diodes Inc.	MMSZ5250B-7-F	Zener	1	\$0.03	 SOD-123 13 mm ²
21.	L2	Coilcraft	SER1360-182KLB	L= 1.8 uH DCR= 2.4 mOhm	1	\$0.72	 SER1360 225 mm ²
22.	M1	STMicroelectronics	STW21N90K5	VdsMax= 900.0 V IdsMax= 18.5 Amps	1	\$3.94	 TO-247 123 mm ²







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
23.	O1	Vishay-Semiconductor	TCMT1107	Optocoupler	1	\$0.21	 SOP-4 44 mm ²
24.	Q1	ON Semiconductor	BC846BLT1G	Bipolar Transistor	1	\$0.02	 SOT-23 14 mm ²
25.	R11	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
26.	R12	Vishay-Dale	CRCW040226K7FKED Series= CRCW..e3	Res= 26.7 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
27.	R13	Vishay-Dale	CRCW04024K99FKED Series= CRCW..e3	Res= 4.99 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
28.	R21	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
29.	R22	Vishay-Dale	CRCW0402681KFKED Series= CRCW..e3	Res= 681.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
30.	Raux	Vishay-Dale	CRCW040210R0FKED Series= CRCW..e3	Res= 10.0 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
31.	Rbias	Panasonic	ERJ-6ENF1372V Series= ERJ-6E	Res= 13.7 kOhm Power= 125.0 mW Tolerance= 1.0%	1	\$0.01	 0805 7 mm ²
32.	Rcs	Vishay-Dale	CRCW04022K00FKED Series= CRCW..e3	Res= 2.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
33.	Rdrv	Vishay-Dale	CRCW04028R66FKED Series= CRCW..e3	Res= 8.66 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
34.	Rfbb	Vishay-Dale	CRCW04023K48FKED Series= CRCW..e3	Res= 3.48 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
35.	Rfbt	Yageo America	RC0603FR-0730KL Series= ?	Res= 30.0 kOhm Power= 100.0 mW Tolerance= 1.0%	1	\$0.01	 0603 5 mm ²
36.	Rled	Vishay-Dale	CRCW040230K9FKED Series= CRCW..e3	Res= 30.9 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
37.	Rsc	Vishay-Dale	CRCW040218K2FKED Series= CRCW..e3	Res= 18.2 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
38.	Rsns	Stackpole Electronics Inc	CSRN2512FKR250 Series= ?	Res= 250.0 mOhm Power= 2.0 W Tolerance= 1.0%	1	\$0.13	 2512 43 mm ²
39.	Rsnu	CUSTOM	CUSTOM Series= ?	Res= 9.7551 kOhm Power= 0.0 W Tolerance= 0.0%	1	NA	CUSTOM 0 mm ²
40.	Rstartup1	Panasonic	ERJ-8ENF2872V Series= ERJ-8E	Res= 28.7 kOhm Power= 250.0 mW Tolerance= 1.0%	1	\$0.01	 1206 11 mm ²
41.	Rstartup2	Panasonic	ERJ-8ENF2872V Series= ERJ-8E	Res= 28.7 kOhm Power= 250.0 mW Tolerance= 1.0%	1	\$0.01	 1206 11 mm ²
42.	Rt	Vishay-Dale	CRCW040230K9FKED Series= CRCW..e3	Res= 30.9 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
43.	Rz	Panasonic	ERJ-6ENF2211V Series= ERJ-6E	Res= 2.21 kOhm Power= 125.0 mW Tolerance= 1.0%	1	\$0.01	 0805 7 mm ²







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
44.	T1	CUSTOM	CUSTOM	Lp= 1.188 mH Rp= 870.0 mOhm Leakage_L= 23.761 μ H Ns1toNp= 0.354 Rs1= 8.6 mOhms Ns2toNp= 0.224 Rs2= 700.0 μ Ohms	1	NA	CUSTOM 0 mm ²
45.	U1	Texas Instruments	UC2844AN	Switcher	1	\$0.64	 P0008A 116 mm ²
46.	VR	Texas Instruments	TL431AIDBVR	Voltage References	1	\$0.07	 R-PDSO-G3 16 mm ²






























Operating Values

#	Name	Value	Category	Description
1.	Cout1 IRMS	3.339 A	Current	Output capacitor1 RMS ripple current
2.	Iin Avg	713.147 mA	Current	Average input current
3.	Iout_DCM	1.103 A	Current	Approximate Current below which DCM mode of operation will begin
4.	Ipri Avg	809.139 mA	Current	Average Current in Primary Winding over the complete Switching Period
5.	Ipri ripple	1.254 A	Current	Ripple Current in the Primary Winding
6.	Ipri ripple pk-pk percentage	62.06 %	Current	Primary Current pk-pk ripple percentage(of Ipri avg during ton only)
7.	Isec Ripple	3.541 A	Current	Ripple Current in the Secondary Winding
8.	T1 Iprim RMS	1.299 A	Current	Transformer Primary RMS Current
9.	T1 Iprim pk	2.648 A	Current	Transformer Primary Peak Current
10.	T1 Is1 RMS	4.488 A	Current	Transformer Secondary1 RMS Current
11.	T1 Is1 pk	7.476 A	Current	Transformer Secondary1 Peak Current
12.	BOM Count	47	General	Total Design BOM count
13.	Daux trr	0.0 ns	General	Auxiliary Diode Reverse Recovery Time
14.	Dsec Vf	500.0 mV	General	Effective Forward Voltage Drop at the Operating Current
15.	Dsec trr	60.0 ns	General	Output Diode Reverse Recovery Time
16.	Dsec2 Vf	500.0 mV	General	Effective Forward Voltage Drop at the Operating Current
17.	Dsnub trr	30.0 ns	General	Snubber Diode Reverse Recovery Time
18.	FootPrint	3.363 k mm ²	General	Total Foot Print Area of BOM components
19.	Frequency	27.832 kHz	General	Switching frequency
20.	Pout	72.0 W	General	Total output power
21.	Tdead	2.653 kns	General	Approximate Dead Time of the Regulator
22.	Toff	18.893 us	General	Approximate Converter Off Time
23.	Ton Act	14.385 us	General	Approximate Converter On Time
24.	Total BOM	\$0.0	General	Total BOM Cost
25.	Tsw	35.93 us	General	Switching Time Period
26.	Vaux	15.476 V	General	Auxiliary Voltage
27.	Vsnub	116.356 V	General	Voltage Across the Snubber
28.	Vout Actual	24.004 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
29.	Vout OP	24.0 V	Op_Point	Operational Output Voltage
30.	Duty Cycle	40.035 %	Op_point	Duty cycle
31.	Efficiency	91.783 %	Op_point	Steady state efficiency
32.	IC Tj	75.095 degC	Op_point	IC junction temperature
33.	ICThetaJA	110.0 degC/W	Op_point	IC junction-to-ambient thermal resistance
34.	IOUT_OP	3.0 A	Op_point	Iout operating point
35.	M1 TJOP	81.744 degC	Op_point	M1 MOSFET junction temperature
36.	Vout p-p	74.357 mV	Op_point	Peak-to-peak output ripple voltage
37.	Cin Pd	8.569 mW	Power	Input capacitor power dissipation
38.	Cout1 Pd	234.079 mW	Power	Output capacitor1 power dissipation
39.	Dsec Pd	750.0 mW	Power	Secondary Diode Power Dissipation
40.	Dsec2 Pd	750.0 mW	Power	Secondary Diode Power Dissipation
41.	IC Pd	273.588 mW	Power	IC power dissipation
42.	L2 Pd	21.6 mW	Power	Average Power Dissipation in the Inductor Over the AC Line Period
43.	M1 Pd	734.889 mW	Power	M1 MOSFET total power dissipation
44.	Paux	14.758 mW	Power	Power Dissipation in Raux and Daux
45.	Pd Rstartup	616.838 mW	Power	Power Dissipation in Rstartup1 and Rstartup2
46.	Rdrv Pd	12.403 μW	Power	Power Dissipation in Gate Drive Resistor
47.	Rfb Pd	17.204 mW	Power	Rfb Power Dissipation
48.	Rsns Pd	421.956 mW	Power	Current Limit Sense Resistor Power Dissipation
49.	Snubber Pd	1.395 W	Power	Snubber Power Dissipation
50.	T1 Pd	3.283 W	Power	Estimated Losses in Transformer

#	Name	Value	Category	Description
51.	Total Pd	0.0 W	Power	Total Power Dissipation
52.	Vout Tolerance	2.137 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable
53.	Vout pp percentage	309.82 m%		Output Voltage ripple percentage

Design Inputs

#	Name	Value	Description
1.	Iout	3.0	Maximum Output Current
2.	Iout1	3.0	Output Current #1
3.	Iout2	1.0	Output Current #2
4.	Iout3	1.0	Output Current #3
5.	VinMax	250.0	Maximum input voltage
6.	VinMin	110.0	Minimum input voltage
7.	Vout	24.0	Output Voltage
8.	Vout1	24.0	Output Voltage #1
9.	Vout2	12.0	Output Voltage #2
10.	Vout3	5.0	Output Voltage #3
11.	base_pn	UC2844A	Texas Instruments Base Part Number
12.	source	DC	Input Source Type
13.	ta	45.0	Ambient temperature

Design Assistance

1. UC2844A Product Folder : <http://www.ti.com/product/UC2844A> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).