


WEBENCH® Design Report







Design : 4466246/57 TPS40170RGYR
TPS40170RGYR 48.0V-60.0V to 12.00V @ 2.0A















Electrical BOM







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cbst	Taiyo Yuden	HMK212B7104KG-T Series= X7R	Cap= 100.0 nF VDC= 100.0 V IRMS= 0.0 A	1	\$0.03	0805 7 mm ²
2.	Cbyp	MuRata	GRM21BR61E475KA12L Series= X5R	Cap= 4.7 uF ESR= 5.189 mOhm VDC= 25.0 V IRMS= 2.03531 A	1	\$0.02	0805 7 mm ²
3.	Ccomp	MuRata	GRM155R61A563KA01D Series= X5R	Cap= 56.0 nF VDC= 10.0 V IRMS= 0.0 A	1	\$0.01	0402 3 mm ²
4.	Ccomp2	MuRata	GRM033R71C122KA01D Series= X7R	Cap= 1.2 nF VDC= 16.0 V IRMS= 0.0 A	1	\$0.01	0201 2 mm ²
5.	Ccomp3	Yageo America	CC0805KRX7R9BB562 Series= X7R	Cap= 5.6 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
6.	Cilim	MuRata	GRM216R71E102KA01D Series= X7R	Cap= 1.0 nF VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
7.	Cin	MuRata	GRM31CR72A105KA01L Series= X7R	Cap= 1.0 uF ESR= 5.334 mOhm VDC= 100.0 V IRMS= 1.55432 A	1	\$0.11	1206_190 11 mm ²
8.	Cldrv	MuRata	GRM033R71C102KA01D Series= X7R	Cap= 1.0 nF VDC= 16.0 V IRMS= 0.0 A	1	\$0.01	0201 2 mm ²
9.	Cout	MuRata	GRM31CR61C226ME15L Series= X5R	Cap= 22.0 uF ESR= 3.637 mOhm VDC= 16.0 V IRMS= 3.4771 A	1	\$0.13	1206_190 11 mm ²
10.	Css	MuRata	GRM033R70J222KA01D Series= X7R	Cap= 2.2 nF VDC= 6.3 V IRMS= 0.0 A	1	\$0.01	0201 2 mm ²


#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
11.	Cvdd	MuRata	GRM188R61C105KA93D Series= X5R	Cap= 1.0 uF ESR= 10.127 mOhm VDC= 16.0 V IRMS= 994.63 mA	1	\$0.01	 0603 5 mm²
12.	Cvin	TDK	C3216X5R2A105K Series= X5R	Cap= 1.0 uF ESR= 5.698 mOhm VDC= 100.0 V IRMS= 0.0 A	1	\$0.07	 1206 11 mm²
13.	L1	Sumida	CDRH127/LDNP-470MC	L= 47.0 µH DCR= 78.0 mOhm	1	\$0.61	 CDRH127 196 mm²
14.	M1	Texas Instruments	CSD19537Q3	VdsMax= 100.0 V IdsMax= 50.0 Amps	1	\$0.75	 TRANS_NexFET_Q3 18 mm²
15.	M2	Infineon Technologies	BSC190N12NS3 G	VdsMax= 120.0 V IdsMax= 44.0 Amps	1	\$0.64	 PG-TDSON-8 55 mm²
16.	Rcomp	Vishay-Dale	CRCW04021K05FKED Series= CRCW..e3	Res= 1.05 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
17.	Rcomp2	Vishay-Dale	CRCW0402200RFKED Series= CRCW..e3	Res= 200.0 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
18.	Rcs	Vishay-Dale	CRCW040211K0FKED Series= CRCW..e3	Res= 11.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
19.	Renb	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
20.	Rent	Vishay-Dale	CRCW040264K9FKED Series= CRCW..e3	Res= 64.9 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
21.	Rfbb	Vishay-Dale	CRCW0402523RFKED Series= CRCW..e3	Res= 523.0 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
22.	Rfbt	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
23.	Rpgood	Vishay-Dale	CRCW0402100KFKED Series= CRCW..e3	Res= 100.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
24.	Rscp	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
25.	Rt	Vishay-Dale	CRCW040226K7FKED Series= CRCW..e3	Res= 26.7 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
26.	Rtrk	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
27.	U1	Texas Instruments	TPS40170RGYR	Switcher	1	\$2.10	 RGY0020A 25 mm²











Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	801.785 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	170.235 mA	Current	Output capacitor RMS ripple current
3.	Iin Avg	438.04 mA	Current	Average input current
4.	L Ipp	589.71 mA	Current	Peak-to-peak inductor ripple current
5.	SW Ipk	2.295 A	Current	Peak switch current
6.	BOM Count	27	General	Total Design BOM count
7.	FootPrint	401.0 mm ²	General	Total Foot Print Area of BOM components
8.	Frequency	348.432 kHz	General	Switching frequency
9.	IC Tolerance	6.0 μ V	General	IC Feedback Tolerance
10.	Pout	24.0 W	General	Total output power
11.	Total BOM	\$4.64	General	Total BOM Cost
12.	Low Freq Gain	71.462 dB	Op_Point	Gain at 10Hz
13.	Vout Actual	12.072 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
14.	Cross Freq	19.718 kHz	Op_point	Bode plot crossover frequency
15.	Duty Cycle	20.119 %	Op_point	Duty cycle
16.	Efficiency	91.316 %	Op_point	Steady state efficiency
17.	Gain Marg	-23.952 dB	Op_point	Bode Plot Gain Margin
18.	IC Tj	76.328 degC	Op_point	IC junction temperature
19.	IOUT_OP	2.0 A	Op_point	Iout operating point
20.	M1 Tj	54.097 degC	Op_point	M1 MOSFET junction temperature
21.	M2 Tj	38.262 degC	Op_point	M2 MOSFET junction temperature
22.	Phase Marg	64.226 deg	Op_point	Bode Plot Phase Margin
23.	VIN_OP	60.0 V	Op_point	Vin operating point
24.	Vout p-p	12.874 mV	Op_point	Peak-to-peak output ripple voltage
25.	Cin Pd	3.429 mW	Power	Input capacitor power dissipation
26.	Cout Pd	105.4 μ W	Power	Output capacitor power dissipation
27.	IC Pd	1.324 W	Power	IC power dissipation
28.	L Pd	390.0 mW	Power	Inductor power dissipation
29.	M1 Pd	436.269 mW	Power	M1 MOSFET total power dissipation
30.	M1 PdCond	22.146 mW	Power	M1 MOSFET conduction losses
31.	M1 PdSw	414.122 mW	Power	M1 MOSFET switching losses
32.	M2 Pd	128.826 mW	Power	M2 MOSFET total power dissipation
33.	M2 PdCond	71.213 mW	Power	M2 MOSFET conduction losses
34.	M2 PdSw	57.613 mW	Power	M2 MOSFET switching losses
35.	Total Pd	2.282 W	Power	Total Power Dissipation
36.	Vout Tolerance	1.921 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	2.0	Maximum Output Current
2.	VinMax	60.0	Maximum input voltage
3.	VinMin	48.0	Minimum input voltage
4.	Vout	12.0	Output Voltage
5.	base_pn	TPS40170	Base Product Number
6.	source	DC	Input Source Type
7.	Ta	30.0	Ambient temperature

Design Assistance

1. **TPS40170** Product Folder : <http://www.ti.com/product/TPS40170> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).