


WEBENCH® Design Report

Design : 4648186/21 LM25011Q1MYX/NOPB
LM25011Q1MYX/NOPB 12.0V-21.0V to 3.00V @ 2.0A




1. This regulator device is qualified for Automotive applications. All passives and other components selected in this design may not be qualified for Automotive applications. The user is required to verify that all components in the design meet the qualification and safety requirements for their specific application. View WEBENCH(R) Disclaimer.

Electrical BOM


#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cbst	MuRata	GRM21BR71E104KA01L Series= X7R	Cap= 100.0 nF VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
2.	Cin	TDK	C1608X7R1V105K080AC Series= X7R	Cap= 1.0 uF ESR= 5.522 mOhm VDC= 35.0 V IRMS= 2.2162 A	1	\$0.05	0603 5 mm ²
3.	Cinx	Taiyo Yuden	GMK212B7105KG-T Series= X7R	Cap= 1.0 uF VDC= 35.0 V IRMS= 0.0 A	1	\$0.05	0805 7 mm ²
4.	Cout	MuRata	GRM188R60G106ME47D Series= X5R	Cap= 10.0 uF ESR= 3.0 mOhm VDC= 4.0 V IRMS= 3.0 A	1	\$0.02	0603 5 mm ²
5.	Css	MuRata	GRM21BR71E104KA01L Series= X7R	Cap= 100.0 nF VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
6.	D1	Diodes Inc.	B340A-13-F	VF@Io= 500.0 mV VRRM= 40.0 V	1	\$0.11	SMA 37 mm ²
7.	L1	Bourns	SDR0805-5R6ML	L= 5.6 uH DCR= 40.0 mOhm	1	\$0.22	SDR0805 96 mm ²
8.	Rfb1	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	0402 3 mm ²
9.	Rfb2	Vishay-Dale	CRCW04021K96FKED Series= CRCW..e3	Res= 1.96 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	0402 3 mm ²

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
10.	Rpgood	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
11.	Rsns	Bourns	CRM0805-FW-R050ELF Series= ?	Res= 50.0 mOhm Power= 250.0 mW Tolerance= 1.0%	1	\$0.10	 0805 7 mm ²
12.	Rt	Vishay-Dale	CRCW040261K9FKED Series= CRCW..e3	Res= 61.9 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
13.	U1	Texas Instruments	LM25011Q1MYX/NOPB	Switcher	1	\$1.40	 MUC10A 24 mm ²


D1 Pd




IC Tj















Duty Cycle









Cin IRMS









Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	681.058 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	143.187 mA	Current	Output capacitor RMS ripple current
3.	IC Ipk	2.248 A	Current	Peak switch current in IC
4.	Iin Avg	364.21 mA	Current	Average input current
5.	L Ipp	496.01 mA	Current	Peak-to-peak inductor ripple current
6.	M1 Irms	802.78 mA	Current	Q lavg
7.	BOM Count	13	General	Total Design BOM count
8.	FootPrint	205.0 mm ²	General	Total Foot Print Area of BOM components
9.	Frequency	1.044 MHz	General	Switching frequency
10.	IC Tolerance	50.0 mV	General	IC Feedback Tolerance
11.	M Vds Act	240.834 mV	General	Voltage drop across the MosFET

#	Name	Value	Category	Description
12.	Pout	6.0 W	General	Total output power
13.	Total BOM	\$2.01	General	Total BOM Cost
14.	D1 Tj	98.919 degC	Op_Point	D1 junction temperature
15.	Vout Actual	3.002 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
16.	Vout OP	3.0 V	Op_Point	Operational Output Voltage
17.	Duty Cycle	16.111 %	Op_point	Duty cycle
18.	Efficiency	78.447 %	Op_point	Steady state efficiency
19.	IC Tj	67.473 degC	Op_point	IC junction temperature
20.	ICThetaJA	48.0 degC/W	Op_point	IC junction-to-ambient thermal resistance
21.	IOUT_OP	2.0 A	Op_point	Iout operating point
22.	VIN_OP	21.0 V	Op_point	Vin operating point
23.	Vout p-p	6.122 mV	Op_point	Peak-to-peak output ripple voltage
24.	Cin Pd	2.561 mW	Power	Input capacitor power dissipation
25.	Cout Pd	61.507 μW	Power	Output capacitor power dissipation
26.	D1 Pd	689.188 mW	Power	Output Diode Power Dissipation
27.	Diode Pd	689.188 mW	Power	Diode power dissipation
28.	IC Pd	780.692 mW	Power	IC power dissipation
29.	L Pd	176.0 mW	Power	Inductor power dissipation
30.	Rsns Pd	142.243 mW	Power	Current Limit Sense Resistor Power Dissipation
31.	Total Pd	1.791 W	Power	Total Power Dissipation
32.	Vout Tolerance	2.33 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	2.0	Maximum Output Current
2.	VinMax	21.0	Maximum input voltage
3.	VinMin	12.0	Minimum input voltage
4.	Vout	3.0	Output Voltage
5.	base_pn	LM25011-Q1	Base Product Number
6.	source	DC	Input Source Type
7.	Ta	30.0	Ambient temperature

Design Assistance

1. Feature Highlights: Automotive Qualified 12V to 14V Vin, 2A Constant On-Time Buck Regulator

2. The LM25011-Q1 is qualified for Automotive applications. All passives and other components selected in this design may not be qualified for Automotive applications. The user is required to verify that all components in the design meet the qualification and safety requirements for their specific application

3. **LM25011-Q1** Product Folder : <http://www.ti.com/product/LM25011%2DQ1> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).