








Device = TPS5431DDAR
Topology = Buck
Created = 7/19/16 7:22:01 AM
BOM Cost = \$2.69
BOM Count = 8
Total Pd = 0.62W















#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
8.	U1	Texas Instruments	TPS5431DDAR	Switcher	1	\$1.75	








R-PDSO-G8 57 mm²









Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	299.943 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	55.18 mA	Current	Output capacitor RMS ripple current
3.	IC Ipk	1.096 A	Current	Peak switch current in IC
4.	Iin Avg	130.86 mA	Current	Average input current
5.	L Ipp	191.15 mA	Current	Peak-to-peak inductor ripple current
6.	M1 Irms	341.781 mA	Current	Q lavg
7.	BOM Count	8	General	Total Design BOM count
8.	FootPrint	262.0 mm ²	General	Total Foot Print Area of BOM components
9.	Frequency	500.0 kHz	General	Switching frequency
10.	IC Tolerance	18.315 mV	General	IC Feedback Tolerance
11.	M Vds Act	39.995 mV	General	Voltage drop across the MosFET

#	Name	Value	Category	Description
12.	Pout	2.0 W	General	Total output power
13.	Total BOM	\$2.69	General	Total BOM Cost
14.	D1 Tj	38.29 degC	Op_Point	D1 junction temperature
15.	Vout Actual	1.994 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
16.	Vout OP	2.0 V	Op_Point	Operational Output Voltage
17.	Cross Freq	12.197 kHz	Op_point	Bode plot crossover frequency
18.	Duty Cycle	11.681 %	Op_point	Duty cycle
19.	Efficiency	76.418 %	Op_point	Steady state efficiency
20.	IC Tj	35.841 degC	Op_point	IC junction temperature
21.	ICThetaJA	33.0 degC/W	Op_point	IC junction-to-ambient thermal resistance
22.	IOUT_OP	1.0 A	Op_point	Iout operating point
23.	Phase Marg	59.448 deg	Op_point	Bode Plot Phase Margin
24.	VIN_OP	20.0 V	Op_point	Vin operating point
25.	Vout p-p	3.06 mV	Op_point	Peak-to-peak output ripple voltage
26.	Cin Pd	269.898 μW	Power	Input capacitor power dissipation
27.	Cout Pd	48.718 μW	Power	Output capacitor power dissipation
28.	Diode Pd	331.61 mW	Power	Diode power dissipation
29.	IC Pd	177.003 mW	Power	IC power dissipation
30.	L Pd	108.24 mW	Power	Inductor power dissipation
31.	Total Pd	617.188 mW	Power	Total Power Dissipation
32.	Vout Tolerance	2.295 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	1.0	Maximum Output Current
2.	VinMax	20.0	Maximum input voltage
3.	VinMin	10.0	Minimum input voltage
4.	Vout	2.0	Output Voltage
5.	base_pn	TPS5431	Base Product Number
6.	source	DC	Input Source Type
7.	Ta	30.0	Ambient temperature

Design Assistance

1. Feature Highlights: 3A, 500kHz Fixed Switching Frequency, Internal Compensation
2. **TPS5431** Product Folder : <http://www.ti.com/product/TPS5431> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).