


WEBENCH® Design Report







Design : 4649473/4 TPS82084SILR
TPS82084SILR 4.0V-6.0V to 3.30V @ 2.0A







Vout = 3.3V
Iout = 2.0A




Electrical BOM

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cin	Taiyo Yuden	LMK212BJ106KG-T Series= X5R	Cap= 10.0 uF VDC= 10.0 V IRMS= 0.0 A	1	\$0.03	0805 7 mm ²
2.	Cout	MuRata	GRM32ER71C226KE18L Series= X7R	Cap= 22.0 uF ESR= 3.0 mOhm VDC= 16.0 V IRMS= 0.0 A	1	\$0.28	1210 15 mm ²
3.	Rfbb	Vishay-Dale	CRCW0402162KFKED Series= CRCW..e3	Res= 162.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	0402 3 mm ²
4.	Rfbt	Yageo America	RC0603FR-07510KL Series= ?	Res= 510.0 kOhm Power= 100.0 mW Tolerance= 1.0%	1	\$0.01	0603 5 mm ²
5.	Rpg	Vishay-Dale	CRCW0402499KFKED Series= CRCW..e3	Res= 499.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	0402 3 mm ²
6.	U1	Texas Instruments	TPS82084SILR	Switcher	1	\$1.65	SIL0008C_SMD 15 mm ²







Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	1.035 A	Current	Input capacitor RMS ripple current
2.	Cout IRMS	397.033 mA	Current	Output capacitor RMS ripple current
3.	Iin Avg	1.171 A	Current	Average input current
4.	L Ipp	1.375 A	Current	Peak-to-peak inductor ripple current
5.	M1 Irms	1.536 A	Current	Q Iavg
6.	BOM Count	6	General	Total Design BOM count
7.	FootPrint	47.0 mm ²	General	Total Foot Print Area of BOM components
8.	Frequency	2.172 MHz	General	Switching frequency
9.	Pout	6.6 W	General	Total output power
10.	Total BOM	\$1.99	General	Total BOM Cost
11.	Vout Actual	3.319 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors

#	Name	Value	Category	Description
12.	Vout OP	3.3 V	Op_Point	Operational Output Voltage
13.	Duty Cycle	56.711 %	Op_point	Duty cycle
14.	Efficiency	93.904 %	Op_point	Steady state efficiency
15.	IC Tj	52.098 degC	Op_point	IC junction temperature
16.	ICThetaJA	70.0 degC/W	Op_point	IC junction-to-ambient thermal resistance
17.	IOUT_OP	2.0 A	Op_point	Iout operating point
18.	VIN_OP	6.0 V	Op_point	Vin operating point
19.	Vout p-p	4.767 mV	Op_point	Peak-to-peak output ripple voltage
20.	Cin Pd	0.0 W	Power	Input capacitor power dissipation
21.	Cout Pd	472.906 μ W	Power	Output capacitor power dissipation
22.	IC Iq Pd	124.245 μ W	Power	IC Iq Pd
23.	IC Pd	315.693 mW	Power	IC power dissipation
24.	Total Pd	428.451 mW	Power	Total Power Dissipation
25.	Vout Tolerance	2.675 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	2.0	Maximum Output Current
2.	VinMax	6.0	Maximum input voltage
3.	VinMin	4.0	Minimum input voltage
4.	Vout	3.3	Output Voltage
5.	base_pn	TPS82084	Base Product Number
6.	source	DC	Input Source Type
7.	Ta	30.0	Ambient temperature

Design Assistance

1. **TPS82084** Product Folder : <http://www.ti.com/product/TPS82084> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).