


WEBENCH® Design Report


Design : 4749713/6 LMZ12001TZ-ADJ/NOPB
LMZ12001TZ-ADJ/NOPB 16.0V-19.0V to 2.00V @ 1.0A





Vout = 2.0V
Iout = 1.0A















Electrical BOM

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cf	Yageo America	CC0805KRX7R9BB223 Series= X7R	Cap= 22.0 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
2.	Cin	MuRata	GRM32ER7YA106KA12L Series= X7R	Cap= 10.0 uF ESR= 2.008 mOhm VDC= 35.0 V IRMS= 4.6772 A	1	\$0.22	1210_280 15 mm ²
3.	Cout	MuRata	GRM31CD80G107ME39L Series= X6T	Cap= 100.0 uF ESR= 4.84 mOhm VDC= 4.0 V IRMS= 4.3381 A	1	\$0.14	1206_190 11 mm ²
4.	Css	MuRata	GRM216R71H103KA01D Series= X7R	Cap= 10.0 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
5.	Renb	Panasonic	ERJ-6ENF2741V Series= ERJ-6E	Res= 2.74 kOhm Power= 125.0 mW Tolerance= 1.0%	1	\$0.01	0805 7 mm ²
6.	Rent	Panasonic	ERJ-6ENF3402V Series= ERJ-6E	Res= 34.0 kOhm Power= 125.0 mW Tolerance= 1.0%	1	\$0.01	0805 7 mm ²
7.	Rfbb	Panasonic	ERJ-6ENF1071V Series= ERJ-6E	Res= 1.07 kOhm Power= 125.0 mW Tolerance= 1.0%	1	\$0.01	0805 7 mm ²
8.	Rfbb	Susumu Co Ltd	RR1220P-162-D Series= RR12	Res= 1.6 kOhm Power= 100.0 mW Tolerance= 0.5%	1	\$0.01	0805 7 mm ²
9.	Ron	Panasonic	ERJ-6ENF3652V Series= ERJ-6E	Res= 36.5 kOhm Power= 125.0 mW Tolerance= 1.0%	1	\$0.01	0805 7 mm ²

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
10.	U1	Texas Instruments	LMZ12001TZ-ADJ/NOPB	Switcher	1	\$4.89	 TZA07A 199 mm ²







Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	318.108 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	121.621 mA	Current	Output capacitor RMS ripple current
3.	IC Ip _k	1.211 A	Current	Peak switch current in IC
4.	Iin Avg	129.72 mA	Current	Average input current
5.	M1 Irms	422.5 mA	Current	Q _{lavg}
6.	BOM Count	10	General	Total Design BOM count
7.	FootPrint	272.0 mm ²	General	Total Foot Print Area of BOM components
8.	Frequency	421.496 kHz	General	Switching frequency
9.	IC Tolerance	20.0 mV	General	IC Feedback Tolerance
10.	M V _{ds} Act	130.0 mV	General	Voltage drop across the MosFET
11.	Pout	2.0 W	General	Total output power

#	Name	Value	Category	Description
12.	Total BOM	\$5.32	General	Total BOM Cost
13.	Vout Actual	1.996 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
14.	Vout OP	2.0 V	Op_Point	Operational Output Voltage
15.	Duty Cycle	11.424 %	Op_point	Duty cycle
16.	Efficiency	81.147 %	Op_point	Steady state efficiency
17.	IC Tj	38.963 degC	Op_point	IC junction temperature
18.	ICThetaJA	19.3 degC/W	Op_point	IC junction-to-ambient thermal resistance
19.	IOUT_OP	1.0 A	Op_point	Iout operating point
20.	VIN_OP	19.0 V	Op_point	Vin operating point
21.	Vout p-p	2.039 mV	Op_point	Peak-to-peak output ripple voltage
22.	Cin Pd	203.194 μ W	Power	Input capacitor power dissipation
23.	Cout Pd	71.591 μ W	Power	Output capacitor power dissipation
24.	IC Pd	464.384 mW	Power	IC power dissipation
25.	Total Pd	464.666 mW	Power	Total Power Dissipation
26.	Vout Tolerance	3.431 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	1.0	Maximum Output Current
2.	VinMax	19.0	Maximum input voltage
3.	VinMin	16.0	Minimum input voltage
4.	Vout	2.0	Output Voltage
5.	base_pn	LMZ12001	Base Product Number
6.	source	DC	Input Source Type
7.	Ta	30.0	Ambient temperature

Design Assistance

1. **LMZ12001** Product Folder : <http://www.ti.com/product/LMZ12001> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).