


WEBENCH® Design Report


Design : 4731873/3 UCC38C44DR
UCC38C44DR 110.0V-250.0V to 5.00V @ 2.0A









1. The EMI filter selected here contains the estimated values. The real numbers will depend on the attenuation needed at a particular frequency.

Electrical BOM



#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	C11	TDK	C5750X6S2W105K Series= X6S	Cap= 1.0 uF ESR= 5.263 mOhm VDC= 400.0 V IRMS= 0.0 A	1	\$1.19	 2220 54 mm ²
2.	C12	AVX	08053C104KAT2A Series= X7R	Cap= 100.0 nF ESR= 280.0 mOhm VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
3.	C13	Samsung Electro-Mechanics	CL21C102JBCNFNC Series= C0G/NP0	Cap= 1.0 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
4.	C21	MuRata	KCM55WR72A156MH01K Series= X7R	Cap= 15.0 uF VDC= 100.0 V IRMS= 0.0 A	1	\$1.51	 KCM55W 59 mm ²
5.	C22	Kemet	C0805C220K3GACTU Series= C0G/NP0	Cap= 22.0 pF VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
6.	C23	Yageo America	CC0805KRX7R9BB821 Series= X7R	Cap= 820.0 pF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
7.	Cbulk	CUSTOM	CUSTOM Series= ?	Cap= 17.8 uF ESR= 1.924 Ohm VDC= 424.26 V IRMS= 220.6 mA	1	NA	CUSTOM 0 mm ²
8.	Ccs	Kemet	C0805C181K5GACTU Series= C0G/NP0	Cap= 180.0 pF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
9.	Cout1	Panasonic	16SVP330M Series= SVP	Cap= 330.0 uF ESR= 16.0 mOhm VDC= 16.0 V IRMS= 4.72 A	1	\$0.39	 SM_RADIAL_10AMM 160 mm²
10.	Cout2	Panasonic	16SVPE180M Series= SVPE	Cap= 180.0 uF ESR= 11.0 mOhm VDC= 16.0 V IRMS= 4.46 A	1	\$0.49	 CAPSMT_62_C10 74 mm²
11.	Cref	AVX	08053C104KAT2A Series= X7R	Cap= 100.0 nF ESR= 280.0 mOhm VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm²
12.	Csc	MuRata	GRM216R71H103KA01D Series= X7R	Cap= 10.0 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm²
13.	Csnub	TDK	C3225X7T2J154K Series= X7T	Cap= 150.0 nF ESR= 11.907 mOhm VDC= 630.0 V IRMS= 0.0 A	1	\$0.19	 1210 15 mm²
14.	Ct	Kemet	C0805C102J5GACTU Series= C0G/NP0	Cap= 1.0 nF ESR= 25.0 mOhm VDC= 50.0 V IRMS= 1.71 A	1	\$0.01	 0805 7 mm²
15.	Cvdd	MuRata	GRM188R71E104KA01D Series= X7R	Cap= 100.0 nF ESR= 30.0 mOhm VDC= 25.0 V IRMS= 1.51 A	1	\$0.01	 0603 5 mm²
16.	Cx	TDK	B32913A5104M000 Series= 2231	Cap= 100.0 nF VDC= 1000.0 V IRMS= 0.0 A	1	\$0.46	 B32913_2650x600x1500 228 mm²
17.	Cy1	TDK	B81123C1102M Series= B81123	Cap= 1.0 nF VDC= 3.0 kV IRMS= 0.0 A	1	\$0.22	 B81123_1800x500x1050 140 mm²
18.	Cy2	TDK	B81123C1102M Series= B81123	Cap= 1.0 nF VDC= 3.0 kV IRMS= 0.0 A	1	\$0.22	 B81123_1800x500x1050 140 mm²







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
19.	Cy3	TDK	B81123C1102M Series= B81123	Cap= 1.0 nF VDC= 3.0 kV IRMS= 0.0 A	1	\$0.22	 B81123_1800x500x1050 140 mm ²
20.	D12	Diodes Inc.	MMSZ5248B-7-F	Zener	1	\$0.04	 SOD-123 13 mm ²
21.	D21	Vishay-Semiconductor	SS12-E3/61T	VF@Io= 500.0 mV VRRM= 20.0 V	1	\$0.08	 SMA 37 mm ²
22.	Dac	Vishay-Semiconductor	DF10SA	VF@Io= 1.1 V VRRM= 1,000.0 V	1	\$0.24	 DF-S 99 mm ²
23.	Daux	ON Semiconductor	MBRB40250TG	VF@Io= 860.0 mV VRRM= 250.0 V	1	\$0.94	 DDPAK 210 mm ²
24.	Dsec	Fairchild Semiconductor	FSV8100V	VF@Io= 670.0 mV VRRM= 100.0 V	1	\$0.21	 TO-277A 56 mm ²
25.	Dsec2	STMicroelectronics	STPS20M100SG-TR	VF@Io= 455.0 mV VRRM= 100.0 V	1	\$1.33	 DDPAK 210 mm ²
26.	Dsnub	Diodes Inc.	MURS160-13-F	VF@Io= 1.25 V VRRM= 600.0 V	1	\$0.11	 SMB 44 mm ²
27.	L1	API Delevan	CM6296R-154	Lp= 150.0 µH Rp= 16.0 mOhm Leakage_L= 1.8 µH Ns1toNp= 1.0 Rs1= 0.0 Ohms	1	\$5.95	 CM6296 833 mm ²
28.	L2	Coilcraft	SER1360-182KLB	L= 1.8 µH DCR= 2.4 mOhm	1	\$0.72	 SER1360 225 mm ²
29.	M1	Fairchild Semiconductor	FDD6N50TM	VdsMax= 500.0 V IdsMax= 6.0 Amps	1	\$0.47	 DPAK 102 mm ²







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
30.	O1	Vishay-Semiconductor	TCMT1109	Optocoupler	1	\$0.21	 SOP-4 44 mm ²
31.	R1	Vishay-Dale	AC03000001009JACCS Series= F_RES	Res= 10.0 Ohm Power= 2.25 W Tolerance= 5.0%	1	\$0.30	 AC03 158 mm ²
32.	R11	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
33.	R12	Vishay-Dale	CRCW04021K65FKED Series= CRCW..e3	Res= 1.65 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
34.	R13	Vishay-Dale	CRCW04024K99FKED Series= CRCW..e3	Res= 4.99 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
35.	R21	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
36.	R22	Vishay-Dale	CRCW040263K4FKED Series= CRCW..e3	Res= 63.4 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
37.	Raux	Vishay-Dale	CRCW040210R0FKED Series= CRCW..e3	Res= 10.0 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
38.	Rbias	Vishay-Dale	CRCW0402205RFKED Series= CRCW..e3	Res= 205.0 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
39.	Rcs	Vishay-Dale	CRCW04022K00FKED Series= CRCW..e3	Res= 2.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
40.	Rdrv	Vishay-Dale	CRCW04027R15FKED Series= CRCW..e3	Res= 7.15 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
41.	Rfbb	Vishay-Dale	CRCW04022K05FKED Series= CRCW..e3	Res= 2.05 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
42.	Rfbt	Yageo America	RC0603FR-076K2L Series= ?	Res= 6.2 kOhm Power= 100.0 mW Tolerance= 1.0%	1	\$0.01	 0603 5 mm ²
43.	Rled	Vishay-Dale	CRCW04022K10FKED Series= CRCW..e3	Res= 2.1 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
44.	Rsc	Vishay-Dale	CRCW040211K0FKED Series= CRCW..e3	Res= 11.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
45.	Rsns	Vishay-Dale	CRCW12062R21FKEA Series= CRCW..e3	Res= 2.21 Ohm Power= 250.0 mW Tolerance= 1.0%	1	\$0.01	 1206 11 mm ²
46.	Rsnu	Panasonic	ERJ-8ENF8662V Series= ERJ-8E	Res= 86.6 kOhm Power= 250.0 mW Tolerance= 1.0%	1	\$0.01	 1206 11 mm ²
47.	Rstartup1	Panasonic	ERJ-8ENF2213V Series= ERJ-8E	Res= 221.0 kOhm Power= 250.0 mW Tolerance= 1.0%	1	\$0.01	 1206 11 mm ²
48.	Rstartup2	Panasonic	ERJ-8ENF2213V Series= ERJ-8E	Res= 221.0 kOhm Power= 250.0 mW Tolerance= 1.0%	1	\$0.01	 1206 11 mm ²
49.	Rt	Vishay-Dale	CRCW04028K66FKED Series= CRCW..e3	Res= 8.66 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
50.	Rx1	Vishay-Semiconductor	CRCW2010200KFKEF Series= ?	Res= 200.0 kOhm Power= 750.0 mW Tolerance= 1.0%	1	\$0.03	 2010 32 mm ²







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
51.	Rx2	Vishay-Semiconductor	CRCW2010200KFKEF Series= ?	Res= 200.0 kOhm Power= 750.0 mW Tolerance= 1.0%	1	\$0.03	 2010 32 mm ²
52.	T1	CUSTOM	CUSTOM	Lp= 2.524 mH Rp= 870.0 mOhm Leakage_L= 50.474 μH Ns1toNp= 0.076 Rs1= 8.6 mOhms Ns2toNp= 0.194 Rs2= 700.0 μOhms	1	NA	CUSTOM 0 mm ²
53.	U1	Texas Instruments	UCC38C44DR	Switcher	1	\$0.60	 D0008A 57 mm ²
54.	VR	Texas Instruments	LMV431CM5/NOPB	Voltage References	1	\$0.16	 R-PDSO-G3 16 mm ²














































Operating Values

#	Name	Value	Category	Description
1.	Cout1 IRMS	1.621 A	Current	Output capacitor1 RMS ripple current
2.	Iin rms	106.53 mA	Current	RMS Input Current
3.	Iout_DCM	788.386 mA	Current	Approximate Current below which DCM mode of operation will begin
4.	Ipri Avg	101.283 mA	Current	Average Current in Primary Winding over the complete Switching Period
5.	Ipri ripple	176.853 mA	Current	Ripple Current in the Primary Winding
6.	Ipri ripple pk-pk percentage	71.278 %	Current	Primary Current pk-pk ripple percentage(of Ipri avg during ton only)
7.	Isec Ripple	2.336 A	Current	Ripple Current in the Secondary Winding
8.	T1 Iprim RMS	161.846 mA	Current	Transformer Primary RMS Current
9.	T1 Iprim pk	336.544 mA	Current	Transformer Primary Peak Current
10.	T1 Is1 RMS	2.574 A	Current	Transformer Secondary1 RMS Current
11.	T1 Is1 pk	4.446 A	Current	Transformer Secondary1 Peak Current
12.	AC Frequency	60.0 Hz	General	Input AC frequency
13.	BOM Count	54	General	Total Design BOM count
14.	Daux trr	0.0 ns	General	Auxiliary Diode Reverse Recovery Time
15.	Dsec Vf	670.0 mV	General	Effective Forward Voltage Drop at the Operating Current
16.	Dsec trr	19.64 ns	General	Output Diode Reverse Recovery Time
17.	Dsec2 Vf	397.923 mV	General	Effective Forward Voltage Drop at the Operating Current
18.	Dsnub trr	50.0 ns	General	Snubber Diode Reverse Recovery Time
19.	FootPrint	3.332 k mm ²	General	Total Foot Print Area of BOM components
20.	Frequency	99.307 kHz	General	Switching frequency
21.	Pout	10.0 W	General	Total output power
22.	Power Factor	1.0	General	Assumed Power Factor for the Application
23.	Tdead	0.0 ns	General	Approximate Dead Time of the Regulator
24.	Toff	6.145 us	General	Approximate Converter Off Time
25.	Ton Act	4.111 us	General	Approximate Converter On Time
26.	Total BOM	\$0.0	General	Total BOM Cost
27.	Tsw	10.07 us	General	Switching Time Period
28.	Vaux	14.513 V	General	Auxiliary Voltage
29.	Vsnub	118.089 V	General	Voltage Across the Snubber
30.	Vout Actual	4.99 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
31.	Vout OP	5.0 V	Op_Point	Operational Output Voltage
32.	Duty Cycle	40.82 %	Op_point	Duty cycle
33.	Efficiency	85.339 %	Op_point	Steady state efficiency
34.	IC Tj	33.004 degC	Op_point	IC junction temperature
35.	ICThetaJA	50.0 degC/W	Op_point	IC junction-to-ambient thermal resistance
36.	IOUT_OP	2.0 A	Op_point	Iout operating point
37.	M1 TJOP	32.659 degC	Op_point	M1 MOSFET junction temperature
38.	Peak Rectified Vin	155.562 V	Op_point	Peak voltage seen at rectified input
39.	Vin_OP_RMS	110.0 V	Op_point	AC Input RMS Voltage
40.	Vout p-p	37.378 mV	Op_point	Peak-to-peak output ripple voltage
41.	Avg Bridge Diode Pd	128.672 mW	Power	Average Power Dissipation in the Bridge Diode over the AC Line Period
42.	Cbulk Pd	65.017 mW	Power	Bulk capacitor power dissipation
43.	Cout1 Pd	42.017 mW	Power	Output capacitor1 power dissipation
44.	Cx Pd	0.0 W	Power	X-cap Power Dissipation
45.	Cy Pd	0.0 W	Power	Y-caps Power Dissipation
46.	Dsec Pd	670.0 mW	Power	Secondary Diode Power Dissipation
47.	Dsec2 Pd	397.923 mW	Power	Secondary Diode Power Dissipation
48.	IC Pd	60.083 mW	Power	IC power dissipation
49.	L1 Pd	667.353 μW	Power	Power Dissipation in the Inductor
50.	L2 Pd	9.6 mW	Power	Average Power Dissipation in the Inductor Over the AC Line Period

#	Name	Value	Category	Description
51.	M1 Pd	32.034 mW	Power	M1 MOSFET total power dissipation
52.	Paux	10.461 mW	Power	Power Dissipation in Raux and Daux
53.	Pd Rstartup	178.91 mW	Power	Power Dissipation in Rstartup1 and Rstartup2
54.	Rdrv Pd	11.553 μ W	Power	Power Dissipation in Gate Drive Resistor
55.	Rfb Pd	3.03 mW	Power	Rfb Power Dissipation
56.	Rsns Pd	57.889 mW	Power	Current Limit Sense Resistor Power Dissipation
57.	Rx Pd	120.961 mW	Power	Total Power Dissipation in Rx1 and Rx2
58.	Snubber Pd	161.698 mW	Power	Snubber Power Dissipation
59.	T1 Pd	159.546 mW	Power	Estimated Losses in Transformer
60.	Total Pd	1.718 W	Power	Total Power Dissipation
61.	Vout Tolerance	2.173 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable
62.	Vout pp percentage	747.553 m%		Output Voltage ripple percentage

Design Inputs

#	Name	Value	Description
1.	Iout	2.0	Maximum Output Current
2.	Iout1	2.0	Output Current #1
3.	Iout2	3.0	Output Current #2
4.	Iout3	5.0	Output Current #3
5.	VinMax	250.0	Maximum input voltage
6.	VinMin	110.0	Minimum input voltage
7.	Vout	5.0	Output Voltage
8.	Vout1	5.0	Output Voltage #1
9.	Vout2	18.0	Output Voltage #2
10.	Vout3	24.0	Output Voltage #3
11.	line_fsw	60.0	Light Output in Lumen
12.	base_pn	UCC38C44	Base Product Number
13.	source	AC	Input Source Type
14.	Ta	30.0	Ambient temperature

Design Assistance

1. **UCC38C44** Product Folder : <http://www.ti.com/product/UCC38C44> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).