


WEBENCH® Design Report

Design : 4743778/9 UC2843N
UC2843N 220.0V-220.0V to 5.00V @ 2.0A






1. The EMI filter selected here contains the estimated values. The real numbers will depend on the attenuation needed at a particular frequency.


Electrical BOM





#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	C11	TDK	C5750X6S2W105K Series= X6S	Cap= 1.0 uF ESR= 5.263 mOhm VDC= 400.0 V IRMS= 0.0 A	1	\$1.19	 2220 54 mm ²
2.	C12	AVX	08053C104KAT2A Series= X7R	Cap= 100.0 nF ESR= 280.0 mOhm VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
3.	C13	Samsung Electro-Mechanics	CL21C102JBCNFNC Series= C0G/NP0	Cap= 1.0 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
4.	C21	CUSTOM	CUSTOM Series= ?	Cap= 11.85 uF VDC= 10.0 V IRMS= 0.0 A	1	NA	CUSTOM 0 mm ²
5.	C22	Kemet	C0805C220K3GACTU Series= C0G/NP0	Cap= 22.0 pF VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
6.	C23	Yageo America	CC0805KRX7R9BB682 Series= X7R	Cap= 6.8 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
7.	Cbulk	CUSTOM	CUSTOM Series= ?	Cap= 4.4501 uF ESR= 7.6943 Ohm VDC= 373.349 V IRMS= 110.3 mA	1	NA	CUSTOM 0 mm ²
8.	Ccs	Kemet	C0805C181K5GACTU Series= C0G/NP0	Cap= 180.0 pF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
9.	Cout1	Panasonic	16SVPG270M Series= ?	Cap= 270.0 uF ESR= 8.0 mOhm VDC= 16.0 V IRMS= 5.8 A	1	\$0.70	 CAPSMT_62_C10 74 mm ²
10.	Cout2	Chemi-Con	APXE100ARA680ME61G Series= PXE	Cap= 68.0 uF ESR= 28.0 mOhm VDC= 10.0 V IRMS= 2.31 A	3	\$0.39	 CAPSMT_62_E61 53 mm ²
11.	Cref	AVX	08053C104KAT2A Series= X7R	Cap= 100.0 nF ESR= 280.0 mOhm VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
12.	Csc	MuRata	GRM216R71H103KA01D Series= X7R	Cap= 10.0 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
13.	Csnub	TDK	C3225X7T2J154K Series= X7T	Cap= 150.0 nF ESR= 11.907 mOhm VDC= 630.0 V IRMS= 0.0 A	1	\$0.19	 1210 15 mm ²
14.	Ct	Kemet	C0805C102J5GACTU Series= C0G/NP0	Cap= 1.0 nF ESR= 25.0 mOhm VDC= 50.0 V IRMS= 1.71 A	1	\$0.01	 0805 7 mm ²
15.	Cvcc	MuRata	GRM188R71E104KA01D Series= X7R	Cap= 100.0 nF ESR= 30.0 mOhm VDC= 25.0 V IRMS= 1.51 A	1	\$0.01	 0603 5 mm ²
16.	Cx	TDK	B32913A5104M000 Series= 2231	Cap= 100.0 nF VDC= 1000.0 V IRMS= 0.0 A	1	\$0.46	 B32913_2650x600x1500 228 mm ²
17.	Cy1	TDK	B81123C1102M Series= B81123	Cap= 1.0 nF VDC= 3.0 kV IRMS= 0.0 A	1	\$0.22	 B81123_1800x500x1050 140 mm ²
18.	Cy2	TDK	B81123C1102M Series= B81123	Cap= 1.0 nF VDC= 3.0 kV IRMS= 0.0 A	1	\$0.22	 B81123_1800x500x1050 140 mm ²







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
19.	Cy3	TDK	B81123C1102M Series= B81123	Cap= 1.0 nF VDC= 3.0 kV IRMS= 0.0 A	1	\$0.22	 B81123_1800x500x1050 140 mm ²
20.	D21	Vishay-Semiconductor	SS12-E3/61T	VF@Io= 500.0 mV VRRM= 20.0 V	1	\$0.08	 SMA 37 mm ²
21.	Dac	Vishay-Semiconductor	DF10SA	VF@Io= 1.1 V VRRM= 1,000.0 V	1	\$0.24	 DF-S 99 mm ²
22.	Daux	NXP Semiconductor	BAS316,115	VF@Io= 1.4 V VRRM= 100.0 V	1	\$0.02	 SOD-323 9 mm ²
23.	Dsec	Diodes Inc.	B540C-13-F	VF@Io= 550.0 mV VRRM= 40.0 V	1	\$0.17	 SMC 83 mm ²
24.	Dsec2	STMicroelectronics	STPS20M100SG-TR	VF@Io= 455.0 mV VRRM= 100.0 V	1	\$1.33	 DDPAK 210 mm ²
25.	Dsnub	Bourns	CD1408-FU1800	VF@Io= 2.5 V VRRM= 800.0 V	1	\$0.13	 Diode_1408 13 mm ²
26.	L1	API Delevan	CM6296R-154	Lp= 150.0 µH Rp= 16.0 mOhm Leakage_L= 1.8 µH Ns1toNp= 1.0 Rs1= 0.0 Ohms	1	\$5.95	 CM6296 833 mm ²
27.	L2	Coilcraft	SER1360-182KLB	L= 1.8 µH DCR= 2.4 mOhm	1	\$0.72	 SER1360 225 mm ²
28.	M1	IXYS	IXTA06N120P	VdsMax= 1.2 kV IdsMax= 600.0 mAmps	1	\$1.43	 DDPAK 210 mm ²
29.	O1	Vishay-Semiconductor	TCMT1109	Optocoupler	1	\$0.21	 SOP-4 44 mm ²
30.	R1	Vishay-Dale	AC03000001009JACCS Series= F_RES	Res= 10.0 Ohm Power= 2.25 W Tolerance= 5.0%	1	\$0.30	 AC03 158 mm ²







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
31.	R11	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
32.	R12	Vishay-Dale	CRCW04021K62FKED Series= CRCW..e3	Res= 1.62 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
33.	R13	Vishay-Dale	CRCW04024K99FKED Series= CRCW..e3	Res= 4.99 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
34.	R21	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
35.	R22	Vishay-Dale	CRCW040216K9FKED Series= CRCW..e3	Res= 16.9 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
36.	Raux	Vishay-Dale	CRCW040210R0FKED Series= CRCW..e3	Res= 10.0 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
37.	Rbias	Vishay-Dale	CRCW0402205RFKED Series= CRCW..e3	Res= 205.0 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
38.	Rcs	Vishay-Dale	CRCW04022K00FKED Series= CRCW..e3	Res= 2.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
39.	Rdrv	Vishay-Dale	CRCW04026R19FKED Series= CRCW..e3	Res= 6.19 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
40.	Rfbb	Yageo America	RT0805BRD071K42L Series= RT0805	Res= 1.42 kOhm Power= 125.0 mW Tolerance= 0.1%	1	\$0.05	 0805 7 mm²
41.	Rfbb	Yageo America	RC0603FR-074K3L Series= ?	Res= 4.3 kOhm Power= 100.0 mW Tolerance= 1.0%	1	\$0.01	 0603 5 mm²
42.	Rled	Vishay-Dale	CRCW04022K05FKED Series= CRCW..e3	Res= 2.05 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
43.	Rsc	Vishay-Dale	CRCW04028K87FKED Series= CRCW..e3	Res= 8.87 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
44.	Rsns	Vishay-Dale	CRCW04024R75FKED Series= CRCW..e3	Res= 4.75 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
45.	Rsnub	Vishay-Dale	CRCW2010820KFKEF Series= ?	Res= 820.0 kOhm Power= 750.0 mW Tolerance= 1.0%	1	\$0.03	 2010 32 mm²
46.	Rstartup1	Panasonic	ERJ-8ENF5492V Series= ERJ-8E	Res= 54.9 kOhm Power= 250.0 mW Tolerance= 1.0%	1	\$0.01	 1206 11 mm²
47.	Rstartup2	Panasonic	ERJ-8ENF5492V Series= ERJ-8E	Res= 54.9 kOhm Power= 250.0 mW Tolerance= 1.0%	1	\$0.01	 1206 11 mm²
48.	Rt	Vishay-Dale	CRCW040217K4FKED Series= CRCW..e3	Res= 17.4 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
49.	Rx1	Vishay-Semiconductor	CRCW2010200KFKEF Series= ?	Res= 200.0 kOhm Power= 750.0 mW Tolerance= 1.0%	1	\$0.03	 2010 32 mm²
50.	Rx2	Vishay-Semiconductor	CRCW2010200KFKEF Series= ?	Res= 200.0 kOhm Power= 750.0 mW Tolerance= 1.0%	1	\$0.03	 2010 32 mm²







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
51.	T1	CUSTOM	CUSTOM	Lp= 10.499 mH Rp= 870.0 mOhm Leakage_L= 209.981 μ H Ns1toNp= 0.026 Rs1= 8.6 mOhms Ns2toNp= 0.057 Rs2= 700.0 μ Ohms	1	NA	CUSTOM 0 mm ²
52.	U1	Texas Instruments	UC2843N	Switcher	1	\$0.64	 P0008A 116 mm ²
53.	VR	Texas Instruments	LMV431CM5/NOPB	Voltage References	1	\$0.16	 R-PDSO-G3 16 mm ²





































Operating Values

#	Name	Value	Category	Description
1.	Cout1 IRMS	2.041 A	Current	Output capacitor1 RMS ripple current
2.	Iin rms	68.033 mA	Current	RMS Input Current
3.	Iout_DCM	1.067 A	Current	Approximate Current below which DCM mode of operation will begin
4.	Ipri Avg	48.312 mA	Current	Average Current in Primary Winding over the complete Switching Period
5.	Ipri ripple	101.292 mA	Current	Ripple Current in the Primary Winding
6.	Ipri ripple pk-pk percentage	101.329 %	Current	Primary Current pk-pk ripple percentage(of Ipri avg during ton only)
7.	Isec Ripple	3.866 A	Current	Ripple Current in the Secondary Winding
8.	T1 Iprim RMS	72.406 mA	Current	Transformer Primary RMS Current
9.	T1 Iprim pk	150.609 mA	Current	Transformer Primary Peak Current

#	Name	Value	Category	Description
10.	T1 Is1 RMS	2.857 A	Current	Transformer Secondary1 RMS Current
11.	T1 Is1 pk	5.748 A	Current	Transformer Secondary1 Peak Current
12.	AC Frequency	60.0 Hz	General	Input AC frequency
13.	BOM Count	55	General	Total Design BOM count
14.	Daux trr	4.0 ns	General	Auxiliary Diode Reverse Recovery Time
15.	Dsec Vf	330.58 mV	General	Effective Forward Voltage Drop at the Operating Current
16.	Dsec trr	0.0 ns	General	Output Diode Reverse Recovery Time
17.	Dsec2 Vf	397.923 mV	General	Effective Forward Voltage Drop at the Operating Current
18.	Dsnub trr	35.0 ns	General	Snubber Diode Reverse Recovery Time
19.	FootPrint	3.243 k mm ²	General	Total Foot Print Area of BOM components
20.	Frequency	98.851 kHz	General	Switching frequency
21.	Pout	10.0 W	General	Total output power
22.	Power Factor	1.0	General	Assumed Power Factor for the Application
23.	Tdead	0.0 ns	General	Approximate Dead Time of the Regulator
24.	Toff	5.303 us	General	Approximate Converter Off Time
25.	Ton Act	4.889 us	General	Approximate Converter On Time
26.	Total BOM	\$0.0	General	Total BOM Cost
27.	Tsw	10.116 us	General	Switching Time Period
28.	Vaux	11.688 V	General	Auxiliary Voltage
29.	Vsnub	334.925 V	General	Voltage Across the Snubber
30.	Vout Actual	4.995 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
31.	Vout OP	5.0 V	Op_Point	Operational Output Voltage
32.	Duty Cycle	48.33 %	Op_point	Duty cycle
33.	Efficiency	66.813 %	Op_point	Steady state efficiency
34.	IC Tj	51.814 degC	Op_point	IC junction temperature
35.	ICThetaJA	110.0 degC/W	Op_point	IC junction-to-ambient thermal resistance
36.	IOUT_OP	2.0 A	Op_point	Iout operating point
37.	M1 TJOP	36.896 degC	Op_point	M1 MOSFET junction temperature
38.	Peak Rectified Vin	311.124 V	Op_point	Peak voltage seen at rectified input
39.	Vin_OP_RMS	220.0 V	Op_point	AC Input RMS Voltage
40.	Vout p-p	30.928 mV	Op_point	Peak-to-peak output ripple voltage
41.	Avg Bridge Diode Pd	60.646 mW	Power	Average Power Dissipation in the Bridge Diode over the AC Line Period
42.	Cbulk Pd	65.004 mW	Power	Bulk capacitor power dissipation
43.	Cout1 Pd	33.319 mW	Power	Output capacitor1 power dissipation
44.	Cx Pd	0.0 W	Power	X-cap Power Dissipation
45.	Cy Pd	0.0 W	Power	Y-caps Power Dissipation
46.	Dsec Pd	330.58 mW	Power	Secondary Diode Power Dissipation
47.	Dsec2 Pd	397.923 mW	Power	Secondary Diode Power Dissipation
48.	IC Pd	198.305 mW	Power	IC power dissipation
49.	L1 Pd	166.838 μW	Power	Power Dissipation in the Inductor
50.	L2 Pd	9.6 mW	Power	Average Power Dissipation in the Inductor Over the AC Line Period
51.	M1 Pd	172.399 mW	Power	M1 MOSFET total power dissipation
52.	Paux	26.865 mW	Power	Power Dissipation in Raux and Daux
53.	Pd Rstartup	3.248 W	Power	Power Dissipation in Rstartup1 and Rstartup2
54.	Rdrv Pd	10.699 μW	Power	Power Dissipation in Gate Drive Resistor
55.	Rfb Pd	4.371 mW	Power	Rfb Power Dissipation
56.	Rsns Pd	24.902 mW	Power	Current Limit Sense Resistor Power Dissipation
57.	Rx Pd	483.845 mW	Power	Total Power Dissipation in Rx1 and Rx2
58.	Snubber Pd	137.464 mW	Power	Snubber Power Dissipation
59.	T1 Pd	149.559 mW	Power	Estimated Losses in Transformer
60.	Total Pd	4.967 W	Power	Total Power Dissipation
61.	Vout Tolerance	1.478 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable
62.	Vout pp percentage	618.556 m%		Output Voltage ripple percentage

Design Inputs

#	Name	Value	Description
1.	Iout	2.0	Maximum Output Current
2.	VinMax	220.0	Maximum input voltage
3.	VinMin	220.0	Minimum input voltage
4.	Vout	5.0	Output Voltage
5.	acFrequency	60.0	Light Output in Lumen
6.	base_pn	UC2843	Texas Instruments Base Part Number
7.	source	AC	Input Source Type
8.	ta	30.0	Ambient temperature

Design Assistance

1. UC2843 Product Folder : <http://www.ti.com/product/UC2843> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).