













WEBENCH® Design Report







Design : 4181735/9 TPS61232DRCR
TPS61232DRCR 3.0V-5.0V to 5.00V @ 1.0A




Electrical BOM

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cin	Taiyo Yuden	LMK212BJ226MG-T Series= X5R	Cap= 22.0 uF VDC= 10.0 V IRMS= 0.0 A	1	\$0.12	 0805 7 mm ²
2.	Cout	Taiyo Yuden	LMK212BJ106KG-T Series= X5R	Cap= 10.0 uF VDC= 10.0 V IRMS= 0.0 A	3	\$0.03	 0805 7 mm ²
3.	Css	MuRata	GRM155R61A154KE19D Series= X5R	Cap= 150.0 nF VDC= 10.0 V IRMS= 0.0 A	1	\$0.01	 0402 3 mm ²
4.	L1	Bourns	SRU1028-1R0Y	L= 1.0 µH DCR= 4.9 mOhm	1	\$0.33	 SRU1028 144 mm ²
5.	U1	Texas Instruments	TPS61232DRCR	Switcher	1	\$1.15	 DRC0010G 16 mm ²







Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	172.683 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	899.226 mA	Current	Output capacitor RMS ripple current
3.	IC Ipk	2.098 A	Current	Peak switch current in IC
4.	Iin Avg	1.801 A	Current	Average input current
5.	L Ipp	598.19 mA	Current	Peak-to-peak inductor ripple current
6.	BOM Count	7	General	Total Design BOM count
7.	FootPrint	190.0 mm ²	General	Total Foot Print Area of BOM components
8.	Frequency	2.0 MHz	General	Switching frequency
9.	Mode	BOOST PWM CCM	General	PWM/PFM Mode
10.	Pout	5.0 W	General	Total output power
11.	Total BOM	\$1.7	General	Total BOM Cost
12.	Duty Cycle	42.341 %	Op_point	Duty cycle
13.	Efficiency	92.55 %	Op_point	Steady state efficiency
14.	IC Tj	48.975 degC	Op_point	IC junction temperature
15.	ICThetaJA	49.1 degC/W	Op_point	IC junction-to-ambient thermal resistance
16.	IOUT_OP	1.0 A	Op_point	Iout operating point
17.	VIN_OP	3.0 V	Op_point	Vin operating point
18.	Vout p-p	8.182 mV	Op_point	Peak-to-peak output ripple voltage
19.	Cin Pd	0.0 W	Power	Input capacitor power dissipation
20.	Cout Pd	0.0 W	Power	Output capacitor power dissipation
21.	IC Pd	386.452 mW	Power	IC power dissipation
22.	L Pd	16.003 mW	Power	Inductor power dissipation
23.	Total Pd	402.479 mW	Power	Total Power Dissipation
24.	Vout Tolerance	2.0 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	1.0	Maximum Output Current
2.	VinMax	5.0	Maximum input voltage

#	Name	Value	Description
3.	VinMin	3.0	Minimum input voltage
4.	Vout	5.0	Output Voltage
5.	base_pn	TPS61232	Base Product Number
6.	source	DC	Input Source Type
7.	Ta	30.0	Ambient temperature

Design Assistance

1. **TPS61232** Product Folder : <http://www.ti.com/product/TPS61232> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).