


WEBENCH® Design Report



Design : 4766207/21 LM25005MHX/NOPB
LM25005MHX/NOPB 22.0V-40.0V to 3.30V @ 2.0A















Electrical BOM







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cboot	Kemet	C0805C223K5RACTU Series= X7R	Cap= 22.0 nF ESR= 125.0 mOhm VDC= 50.0 V IRMS= 645.0 mA	1	\$0.01	0805 7 mm ²
2.	Cbyp	AVX	08053C104KAT2A Series= X7R	Cap= 100.0 nF ESR= 280.0 mOhm VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
3.	Ccomp	MuRata	GRM033R71E152KA01D Series= X7R	Cap= 1.5 nF VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	0201 2 mm ²
4.	Ccomp2	Kemet	C0805C220K3GACTU Series= C0G/NP0	Cap= 22.0 pF VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
5.	Cin	MuRata	GRM31CR72A105KA01L Series= X7R	Cap= 1.0 uF ESR= 5.334 mOhm VDC= 100.0 V IRMS= 1.55432 A	1	\$0.11	1206_190 11 mm ²
6.	Cout	MuRata	GRM31CR60J107ME39L Series= X5R	Cap= 100.0 uF ESR= 4.885 mOhm VDC= 6.3 V IRMS= 4.4118 A	1	\$0.14	1206_190 11 mm ²
7.	Cramp	AVX	08055A101JAT2A Series= C0G/NP0	Cap= 100.0 pF ESR= 356.0 mOhm VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	0805 7 mm ²
8.	Css	MuRata	GRM155R71E822KA01D Series= X7R	Cap= 8.2 nF VDC= 25.0 V IRMS= 0.0 A	1	\$0.01	0402 3 mm ²
9.	D1	Diodes Inc.	B360A-13-F	VF@Io= 700.0 mV VRRM= 60.0 V	1	\$0.12	SMA 37 mm ²

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
10.	L1	Bourns	SRU1038-100Y	L= 10.0 μ H DCR= 25.0 mOhm	1	\$0.33	 SRU1038 144 mm ²
11.	Rcomp	Panasonic	ERJ-6ENF1742V Series= ERJ-6E	Res= 17.4 kOhm Power= 125.0 mW Tolerance= 1.0%	1	\$0.01	 0805 7 mm ²
12.	Rfb1	Panasonic	ERJ-6ENF1001V Series= ERJ-6E	Res= 1000.0 Ohm Power= 125.0 mW Tolerance= 1.0%	1	\$0.01	 0805 7 mm ²
13.	Rfb2	Panasonic	ERJ-6ENF1691V Series= ERJ-6E	Res= 1.69 kOhm Power= 125.0 mW Tolerance= 1.0%	1	\$0.01	 0805 7 mm ²
14.	Rt	Panasonic	ERJ-6ENF8661V Series= ERJ-6E	Res= 8.66 kOhm Power= 125.0 mW Tolerance= 1.0%	1	\$0.01	 0805 7 mm ²
15.	U1	Texas Instruments	LM25005MHX/NOPB	Switcher	1	\$1.40	 MXA20A 71 mm ²









Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	554.885 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	171.278 mA	Current	Output capacitor RMS ripple current
3.	IC Ipk	2.295 A	Current	Peak switch current in IC
4.	Iin Avg	200.95 mA	Current	Average input current
5.	L Ipp	593.32 mA	Current	Peak-to-peak inductor ripple current
6.	M1 Irms	608.045 mA	Current	Q lavg
7.	BOM Count	15	General	Total Design BOM count
8.	FootPrint	334.0 mm ²	General	Total Foot Print Area of BOM components
9.	Frequency	571.723 kHz	General	Switching frequency
10.	IC Tolerance	18.0 mV	General	IC Feedback Tolerance
11.	M Vds Act	172.112 mV	General	Voltage drop across the MosFET

#	Name	Value	Category	Description
12.	Mode	CCM	General	Conduction Mode
13.	Pout	6.6 W	General	Total output power
14.	Total BOM	\$2.2	General	Total BOM Cost
15.	D1 Tj	106.255 degC	Op_Point	D1 junction temperature
16.	Vout Actual	3.295 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
17.	Vout OP	3.3 V	Op_Point	Operational Output Voltage
18.	Duty Cycle	9.243 %	Op_point	Duty cycle
19.	Efficiency	82.11 %	Op_point	Steady state efficiency
20.	IC Tj	52.548 degC	Op_point	IC junction temperature
21.	ICThetaJA	40.0 degC/W	Op_point	IC junction-to-ambient thermal resistance
22.	IOUT_OP	2.0 A	Op_point	Iout operating point
23.	VIN_OP	40.0 V	Op_point	Vin operating point
24.	Vout p-p	3.273 mV	Op_point	Peak-to-peak output ripple voltage
25.	Cin Pd	1.642 mW	Power	Input capacitor power dissipation
26.	Cout Pd	143.307 μ W	Power	Output capacitor power dissipation
27.	Diode Pd	762.553 mW	Power	Diode power dissipation
28.	IC Pd	563.705 mW	Power	IC power dissipation
29.	L Pd	110.0 mW	Power	Inductor power dissipation
30.	Total Pd	1.438 W	Power	Total Power Dissipation
31.	Vout Tolerance	2.757 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	2.0	Maximum Output Current
2.	VinMax	40.0	Maximum input voltage
3.	VinMin	22.0	Minimum input voltage
4.	Vout	3.3	Output Voltage
5.	base_pn	LM25005	Base Product Number
6.	source	DC	Input Source Type
7.	Ta	30.0	Ambient temperature

Design Assistance

1. **LM25005** Product Folder : <http://www.ti.com/product/LM25005> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).