


WEBENCH® Design Report





Design : 4766207/19 TPS54260DGQR
TPS54260DGQR 40.0V-60.0V to 3.30V @ 2.0A















Electrical BOM


#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cboot	MuRata	GRM155R61A104KA01D Series= X5R	Cap= 100.0 nF VDC= 10.0 V IRMS= 0.0 A	1	\$0.01	 0402 3 mm ²
2.	Ccomp	MuRata	GRM033R61A822KA01D Series= X5R	Cap= 8.2 nF VDC= 10.0 V IRMS= 0.0 A	1	\$0.01	 0201 2 mm ²
3.	Ccomp2	MuRata	GRM1555C1H6R2CA01D Series= C0G/NP0	Cap= 6.2 pF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0402 3 mm ²
4.	Cin	TDK	C3225X7R2A225K230AB Series= X7R	Cap= 2.2 uF ESR= 1.73 mOhm VDC= 100.0 V IRMS= 5.5932 A	1	\$0.19	 1210_250 15 mm ²
5.	Cout	MuRata	GRM31CR60J107ME39L Series= X5R	Cap= 100.0 uF ESR= 4.885 mOhm VDC= 6.3 V IRMS= 4.4118 A	2	\$0.14	 1206_190 11 mm ²
6.	Css	Yageo America	CC0805KRX7R9BB682 Series= X7R	Cap= 6.8 nF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
7.	D1	Diodes Inc.	B370-13-F	VF@Io= 790.0 mV VRRM= 70.0 V	1	\$0.22	 SMC 83 mm ²
8.	L1	Bourns	SRR1208-270ML	L= 27.0 uH DCR= 62.0 mOhm	1	\$0.37	 SRR1208 216 mm ²
9.	Rcomp	Vishay-Dale	CRCW040234K0FKED Series= CRCW..e3	Res= 34.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
10.	RenB	Vishay-Dale	CRCW04023K83FKED Series= CRCW..e3	Res= 3.83 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
11.	RenT	Vishay-Dale	CRCW0402105KFKED Series= CRCW..e3	Res= 105.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
12.	Rfbb	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
13.	Rfbt	Vishay-Dale	CRCW040231K6FKED Series= CRCW..e3	Res= 31.6 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
14.	Rt	Vishay-Dale	CRCW0402576KFKED Series= CRCW..e3	Res= 576.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm²
15.	U1	Texas Instruments	TPS54260DGQR	Switcher	1	\$1.80	 S-PDSO-G10 24 mm²









Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	487.509 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	180.416 mA	Current	Output capacitor RMS ripple current
3.	IC IpK	2.0 A	Current	Peak switch current in IC
4.	Iin Avg	147.02 mA	Current	Average input current
5.	L Ipp	624.98 mA	Current	Peak-to-peak inductor ripple current
6.	BOM Count	16	General	Total Design BOM count
7.	FootPrint	392.0 mm ²	General	Total Foot Print Area of BOM components
8.	Frequency	221.44 kHz	General	Switching frequency
9.	Mode	CCM	General	Conduction Mode
10.	Pout	6.6 W	General	Total output power
11.	Total BOM	\$2.96	General	Total BOM Cost
12.	D1 Tj	84.074 degC	Op_Point	D1 junction temperature
13.	Low Freq Gain	83.842 dB	Op_Point	Gain at 10Hz
14.	Vout Actual	3.328 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
15.	Vout OP	3.3 V	Op_Point	Operational Output Voltage
16.	Cross Freq	21.733 kHz	Op_point	Bode plot crossover frequency
17.	Duty Cycle	6.59 %	Op_point	Duty cycle
18.	Efficiency	74.818 %	Op_point	Steady state efficiency
19.	Gain Marg	-17.369 dB	Op_point	Bode Plot Gain Margin
20.	IC Tj	71.292 degC	Op_point	IC junction temperature
21.	ICThetaJA	62.5 degC/W	Op_point	IC junction-to-ambient thermal resistance
22.	IOUT_OP	2.0 A	Op_point	Iout operating point
23.	Phase Marg	63.25 deg	Op_point	Bode Plot Phase Margin
24.	VIN_OP	60.0 V	Op_point	Vin operating point
25.	Vout p-p	2.571 mV	Op_point	Peak-to-peak output ripple voltage
26.	Cin Pd	411.16 μW	Power	Input capacitor power dissipation
27.	Cout Pd	79.503 μW	Power	Output capacitor power dissipation
28.	Diode Pd	1.287 W	Power	Diode power dissipation
29.	IC Pd	660.666 mW	Power	IC power dissipation
30.	L Pd	272.8 mW	Power	Inductor power dissipation
31.	Total Pd	2.221 W	Power	Total Power Dissipation

#	Name	Value	Category	Description
32.	Vout Tolerance	2.55 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	2.0	Maximum Output Current
2.	VinMax	60.0	Maximum input voltage
3.	VinMin	40.0	Minimum input voltage
4.	Vout	3.3	Output Voltage
5.	base_pn	TPS54260	Base Product Number
6.	source	DC	Input Source Type
7.	Ta	30.0	Ambient temperature

Design Assistance

1. **TPS54260** Product Folder : <http://www.ti.com/product/TPS54260> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).