


WEBENCH® Design Report





Design : 4640646/1 TPS54231DR
TPS54231DR 14.0V-22.0V to 3.30V @ 2.0A















Electrical BOM






#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cboot	MuRata	GRM155R61A104KA01D Series= X5R	Cap= 100.0 nF VDC= 10.0 V IRMS= 0.0 A	1	\$0.01	 0402 3 mm ²
2.	Ccomp	MuRata	GRM1555C1H511JA01D Series= C0G/NP0	Cap= 510.0 pF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0402 3 mm ²
3.	Ccomp2	Kemet	C0805C100K5GACTU Series= C0G/NP0	Cap= 10.0 pF VDC= 50.0 V IRMS= 0.0 A	1	\$0.01	 0805 7 mm ²
4.	Cin	MuRata	GRM32ER71H475KA88L Series= X7R	Cap= 4.7 uF ESR= 2.0 mOhm VDC= 50.0 V IRMS= 5.35 A	2	\$0.19	 1210 15 mm ²
5.	Cout	MuRata	GRM31CR60J107ME39L Series= X5R	Cap= 100.0 uF ESR= 4.885 mOhm VDC= 6.3 V IRMS= 4.4118 A	1	\$0.14	 1206_190 11 mm ²
6.	Css	MuRata	GRM033R61A822KA01D Series= X5R	Cap= 8.2 nF VDC= 10.0 V IRMS= 0.0 A	1	\$0.01	 0201 2 mm ²
7.	D1	Diodes Inc.	B340A-13-F	VF@Io= 500.0 mV VRRM= 40.0 V	1	\$0.11	 SMA 37 mm ²
8.	L1	Bourns	SRN8040-100M	L= 10.0 uH DCR= 50.0 mOhm	1	\$0.22	 SRN8040 100 mm ²
9.	Rcomp	Vishay-Dale	CRCW040284K5FKED Series= CRCW..e3	Res= 84.5 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
10.	RenB	Vishay-Dale	CRCW040229K4FKED Series= CRCW..e3	Res= 29.4 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
11.	RenT	Vishay-Dale	CRCW0402169KFKED Series= CRCW..e3	Res= 169.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
12.	Rfbb	Yageo America	RT0805BRD073K28L Series= RT0805	Res= 3.28 kOhm Power= 125.0 mW Tolerance= 0.1%	1	\$0.05	0805 7 mm ²
13.	Rfbt	Vishay-Dale	CRCW040210K2FKED Series= CRCW..e3	Res= 10.2 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	0402 3 mm ²
14.	U1	Texas Instruments	TPS54231DR	Switcher	1	\$0.55	

D0008A 57 mm²







Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	702.161 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	157.694 mA	Current	Output capacitor RMS ripple current
3.	IC Ipk	2.273 A	Current	Peak switch current in IC
4.	Iin Avg	365.58 mA	Current	Average input current
5.	L Ipp	546.27 mA	Current	Peak-to-peak inductor ripple current
6.	M1 Irms	816.11 mA	Current	Q lavg
7.	BOM Count	15	General	Total Design BOM count
8.	FootPrint	268.0 mm ²	General	Total Foot Print Area of BOM components
9.	Frequency	570.0 kHz	General	Switching frequency
10.	M Vds Act	125.046 mV	General	Voltage drop across the MosFET
11.	Mode	CCM	General	Conduction Mode

#	Name	Value	Category	Description
12.	Pout	6.6 W	General	Total output power
13.	Total BOM	\$1.53	General	Total BOM Cost
14.	D1 Tj	98.476 degC	Op_Point	D1 junction temperature
15.	Low Freq Gain	66.675 dB	Op_Point	Gain at 10Hz
16.	Vout Actual	3.288 V	Op_Point	Vout Actual calculated based on selected voltage divider resistors
17.	Vout OP	3.3 V	Op_Point	Operational Output Voltage
18.	Cross Freq	28.485 kHz	Op_point	Bode plot crossover frequency
19.	Duty Cycle	16.651 %	Op_point	Duty cycle
20.	Efficiency	82.062 %	Op_point	Steady state efficiency
21.	Gain Marg	-19.614 dB	Op_point	Bode Plot Gain Margin
22.	IC Tj	83.734 degC	Op_point	IC junction temperature
23.	ICThetaJA	100.0 degC/W	Op_point	IC junction-to-ambient thermal resistance
24.	IOUT_OP	2.0 A	Op_point	Iout operating point
25.	Phase Marg	57.16 deg	Op_point	Bode Plot Phase Margin
26.	VIN_OP	22.0 V	Op_point	Vin operating point
27.	Vout p-p	3.016 mV	Op_point	Peak-to-peak output ripple voltage
28.	Cin Pd	493.031 μ W	Power	Input capacitor power dissipation
29.	Cout Pd	121.477 μ W	Power	Output capacitor power dissipation
30.	Diode Pd	684.756 mW	Power	Diode power dissipation
31.	IC Pd	537.34 mW	Power	IC power dissipation
32.	L Pd	220.0 mW	Power	Inductor power dissipation
33.	Total Pd	1.443 W	Power	Total Power Dissipation
34.	Vout Tolerance	4.362 %		Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable

Design Inputs

#	Name	Value	Description
1.	Iout	2.0	Maximum Output Current
2.	VinMax	22.0	Maximum input voltage
3.	VinMin	14.0	Minimum input voltage
4.	Vout	3.3	Output Voltage
5.	base_pn	TPS54231	Base Product Number
6.	source	DC	Input Source Type
7.	Ta	30.0	Ambient temperature

Design Assistance

1. **TPS54231** Product Folder : <http://www.ti.com/product/TPS54231> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).