























Device = TPS92512DGQR
Topology = Buck
Created = 9/29/16 7:29:23 PM
BOM Cost = \$1.06
BOM Count = 17
Total Pd = 0.85W


#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
11.	Riadj2	Vishay-Dale	CRCW04021K00FKED Series= CRCW..e3	Res= 1000.0 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
12.	Rsense	Rohm	MCR25JZHFLR430 Series= MCR25	Res= 430.0 mOhm Power= 500.0 mW Tolerance= 1.0%	1	\$0.03	 1210 15 mm ²
13.	Rsense1	Vishay-Dale	CRCW04021K00FKED Series= CRCW..e3	Res= 1000.0 Ohm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
14.	Rt	Vishay-Dale	CRCW0402162KFKED Series= CRCW..e3	Res= 162.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
15.	Ruvlob	Vishay-Dale	CRCW04025K49FKED Series= CRCW..e3	Res= 5.49 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
16.	Ruvlot	Vishay-Dale	CRCW040297K6FKED Series= CRCW..e3	Res= 97.6 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	 0402 3 mm ²
17.	U1	Texas Instruments	TPS92512DGQR	Switcher	1	\$0.55	 DGQ0010D_N 24 mm ²











Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	338.77 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	95.904 mA	Current	Output capacitor RMS ripple current
3.	IC Ipk	866.111 mA	Current	Peak switch current in IC
4.	Iin Avg	273.8 mA	Current	Average input current
5.	L Ipp	332.22 mA	Current	Peak-to-peak inductor ripple current
6.	LED Ipp	12.165 mA	Current	LED Ripple Current
7.	BOM Count	17	General	Total Design BOM count
8.	FootPrint	187.0 mm ²	General	Total Foot Print Area of BOM components
9.	Frequency	696.429 kHz	General	Switching frequency
10.	IC Tolerance	0.0 V	General	IC Feedback Tolerance
11.	Mode	CCM	General	Conduction Mode
12.	Pout	8.05 W	General	Total output power
13.	Total BOM	\$1.06	General	Total BOM Cost
14.	Vout OP	11.5 V	Op_Point	Operational Output Voltage
15.	Cross Freq	2.799 kHz	Op_point	Bode plot crossover frequency
16.	Duty Cycle	37.436 %	Op_point	Duty cycle
17.	Efficiency	90.28 %	Op_point	Steady state efficiency
18.	IC Tj	49.542 degC	Op_point	IC junction temperature
19.	ICThetaJA	66.7 degC/W	Op_point	IC junction-to-ambient thermal resistance
20.	IOUT_OP	700.0 mA	Op_point	Iout operating point
21.	LED Rd	13.81 Ohm	Op_point	LED DynamicResistance
22.	Phase Marg	90.432 deg	Op_point	Bode Plot Phase Margin
23.	VIN_OP	32.0 V	Op_point	Vin operating point
24.	Cin Pd	114.765 μW	Power	Input capacitor power dissipation
25.	Cout Pd	50.716 μW	Power	Output capacitor power dissipation
26.	D1 Pd	233.397 mW	Power	Output Diode Power Dissipation
27.	IC Pd	292.98 mW	Power	IC power dissipation
28.	L Pd	114.496 mW	Power	Inductor power dissipation
29.	Rsense Pd	210.7 mW	Power	LED Current Rns Power Dissipation
30.	Total Pd	851.628 mW	Power	Total Power Dissipation
31.	Start Voltage	22.624 V	UVLO	Start Voltage with External UVLO Resistors
32.	Stop Voltage	21.796 V	UVLO	Stop Voltage with External UVLO Resistors
33.	Converter On Time	534.797 ns		Approximate Converter On Time

Design Inputs

#	Name	Value	Description
1.	Iout	700.0 m	Maximum Output Current
2.	VinMax	32.0	Maximum input voltage
3.	VinMin	24.0	Minimum input voltage
4.	Vout	11.5	Output Voltage
5.	application	LED_DRIVER	LED Application
6.	base_pn	TPS92512	Base Product Number
7.	LED_Architect	N	LED Architect Project
8.	ledparallel	1.0	Number of LED in parallel
9.	ledpartnumber	XHP50A-00-0000-0D0B140CP	LED Part number
10.	ledseries	1.0	Number of LED in series
11.	line_fsw	60.0	AC Line Frequency
12.	source	DC	Input Source Type
13.	Ta	30.0	Ambient temperature

Design Assistance

1. **TPS92512** Product Folder : <http://www.ti.com/product/TPS92512> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).